

Touch-MyDesign

Display One

8-Button Capacitive Touch Panel with LCD Display

ZVI-TMDD

Application Program Version: [2.0]
User Manual Version: [2.0]_a

www.zennio.com

CONTENTS

Contents	2
Document Updates	4
1 Introduction	5
1.1 TMD-Display	5
1.2 TMD-Display One.....	7
1.3 Installation.....	8
2 Configuration	10
2.1 Default Configuration.....	10
2.2 General	12
2.2.1 CONFIGURATION	12
2.2.2 Temperature Sensor	14
2.2.3 Screensaver.....	14
2.2.4 LEDs & Display	15
2.2.5 Sounds	18
2.2.6 ADVANCED.....	21
2.2.7 Translations	22
2.2.8 Touch Locking	24
2.2.9 Cleaning Function	25
2.2.10 Welcome Greeting.....	27
2.2.11 Welcome Back Object.....	28
2.2.12 Central Area	30
2.3 Buttons	32
2.3.1 CONFIGURATION	32

2.3.2	Disabled	35
2.3.3	Pair	36
2.3.4	Individual	55
2.4	Display	68
2.4.1	CONFIGURATION	68
2.4.2	Disabled	71
2.4.3	Single.....	71
2.4.4	Double.....	84
2.4.5	Borders	85
2.5	Inputs.....	87
2.6	Thermostat.....	88
ANNEX I: LED Illumination Modes.....		89
ANNEX II: Communication Objects		92

DOCUMENT UPDATES

Version	Changes	Page(s)
[2.0]_a	Changes in the application program: <ul style="list-style-type: none"> • New frequency for the alternation of time and temperature during the screensaver. • Minor revision of parameter and object names. • Revision of the Night Mode function. • New On/Off functions in the dimming control. • Improvement of the fan control functionality. • New motion detection function. 	-
	Minor text changes	-
	Update of “night mode” feature description.	16
	Extension of fan control feature.	39, 52
	Update of dimming control description.	36, 43, 56, 64
	Motion detection function.	87
	Update of the table of LED illumination modes.	90
	Update of the communication object table.	92 - 104

1 INTRODUCTION

1.1 TMD-DISPLAY

TMD-Display is an evolution of Touch-MyDesign Plus, the KNX **multifunction capacitive touch switch** from Zennio.

TMD-Display provides **eight capacitive buttons** aligned in 2 columns of 4 buttons each, **LEDs** to indicate user presses or states, and a **wide display** on the top of the front panel, as in ZAS and Roll-ZAS from Zennio.

TMD-Display is a **fully customisable** solution for the room control, including hotel rooms, offices or any other environment where the user needs to control climate systems, lighting, blinds, scenes, etc.

The versatility of the above functions is enhanced by the built-in **analogue/digital inputs**, the **internal temperature sensor** and the **thermostat** function, as well as an elegant and **fully customisable design of the front glass** – customers can choose their button icons, texts and colours and even personalise the background with their pictures, logos, etc.

Moreover, the **display** offers the possibility to show useful information to the user about the control states and object values.




Figure 1 TMD-Display.

The most outstanding features of TMD-Display are:

- **1.8"** back-lit display with a resolution of **128x64** pixels.
- **Fully customisable** design of the front glass.
- **8 touch buttons** which can operate as individual or pair controls.
- **Light indicator (LED)** for every button, the state of which (on or off) can depend on different factors according to the user's needs.
- **Buzzer** for an audible acknowledgement of user actions (with the possibility of disabling it either by parameter or by object).
- Possibility of **locking / unlocking the touch panel** through binary orders or scenes, and of setting a timed/automatic locking of the device (**cleaning function**).
- **Welcome greeting on the display** and **Welcome Back object** (binary or scene).
- **Central touch area** with a customisable object sending when pressed.
- **Screensaver** function.
- Up to **5 switchable languages** for the displayed texts.
- **Two analogue/digital inputs** (temperature probes, additional switches, etc.).
- **Thermostat** function.
- Built-in **temperature sensor**.
- **Motion detection function**, by connecting the corresponding accessory.

1.2 TMD-DISPLAY ONE

The TMD-Display One application program brings the user the possibility to configure their TMD-Display as a **single-page user interface**.

This means that the capacitive buttons and the LCD display will perform the same functions anytime, making it possible to provide the user with an easy-to-use interface, with no menus or alternating pages.

Because of this, the design of the front glass can contain icons specific enough as to make the function of the touch buttons evident at a simple glance.

Some of the available functions are:

- On the touch buttons:
 - **Pair button functions:** numeric counter, light dimmer, shutter controller, temperature setpoint, etc.
 - **Individual button functions:** binary switch, hold & release, scenes, light dimmer, shutter controller, numeric constants, etc.
- On the display:
 - **Single-box indicator:** icon, number, text, time of day, climate, etc.
 - **Double-box indicator:** icon, number, text, time of day, climate, etc.

In addition to these functions, TMD-Display One incorporates all the features already mentioned in 1.1.

1.3 INSTALLATION




Figure 2 TMD-Display One. Installation Process.

To install the device, it is first necessary to mount the metallic plate into a square/round standard appliance box through the suitable screws. Next, TMD-Display is connected to the KNX bus through the corresponding terminal on the rear side of the device, and then the input terminal is as well connected to the rear of the device.

Once the input terminal and the KNX terminal are connected, the device can be easily mounted on the metallic plate by the action of the built-in magnets. After that, it is necessary to slide it downwards to fix it through the security anchorage system.

Finally, it is advisable to check that the device is properly installed, and that only its profile becomes visible from above, from below and from both sides (the metallic plate should be completely hidden).

This device does not need any external supply, as it is powered through the KNX bus.




Figure 3 Element diagram.

The programming button (4) can be pressed with the help of a thin screw to set the device into the **Programming Mode**. After a short press, the programming LED (5) will light in red. Note that if this button is held while plugging the device into the KNX bus, the device will enter the **Safe Mode**. The LED will then blink in red.

Note: *whenever the device recovers the bus power, an immediate self-calibration process of the touch panel takes place. Please ensure to avoid touching the front glass while powering the device. If undesired effects arise during normal use, please disconnect the device from the bus and connect it again, making sure that the front glass is not touched during this process.*

For detailed information about the technical features of the device and for safety instructions and on the installation process, please refer to the **Datasheet** bundled with the original packaging of the device and also available at www.zennio.com.

2 CONFIGURATION

2.1 DEFAULT CONFIGURATION

To make the device perform the desired functions, several options need to be parameterised, either related to its **general behaviour** (screensaver, sounds, LEDs and display brightness levels...) or to **advanced features** (lock procedure of the touch panel, cleaning function, welcome greeting on the display, welcome back object, etc.).

Some of the above options are common to other Zennio devices such as Touch-MyDesign, Roll-ZAS or Z41, while others are specific for TMD-Display.

On the other hand, TMD-Display features two opto-coupled inputs, each of which may be independently configured as a **switch/sensor**, a **push-button** or a **temperature probe** or **motion detector**, so that external accessories can be connected to the device.

In the particular case of an external temperature probe (such as model **ZN1AC-NTC68** from Zennio), it will be possible to use it with independence of the built-in temperature sensor of the device, which implements its own communication objects and can be enabled and disabled in parameters.

ETS PARAMETERISATION




Figure 4 General.

After importing the corresponding database in ETS and adding the device into the topology of the project, the configuration process begins by right-clicking into the device and selecting *Edit parameters*.

This will bring the window shown in Figure 4, which contains the following tabs:

- **General:** contains the parameters that define the general behaviour of the device and that enable/disable additional features such as the thermostat or the external inputs. See section 2.2 for details.

- **Buttons:** contains the parameters involved in the configuration of the touch buttons of the device. See section 2.3 for details.
- **Display:** contains the parameters related to the configuration of the display of the device. See section 2.4 for details.

Depending on the configuration, other tabs may show in the tab tree on the left.

These tabs will be explained in the next sections.

2.2 GENERAL

As shown in Figure 5, the “General” tab only contains one sub-tab by default: “Configuration”. However, it may include other tabs depending on the parameterisation.

2.2.1 CONFIGURATION




Figure 5. General - Configuration

This tab shows the following parameters:

- **Buttons:** read-only parameter to make it evident that the “Buttons” tab is always enabled in the tab tree on the left. See section 2.3 for details.
- **Display:** read-only parameter to make it evident that the “Display” tab is always enabled in the tab tree on the left. See section 2.4 for details.
- **Inputs:** enables or disables the “Inputs” tab in the tree on the left, depending on whether the device will or will not be connected any external accessories. See section 2.5 for details.
- **Thermostat:** enables or disables the “Thermostat” tab in the tree on the left. See section 2.6 for details.
- **Internal temperature sensor:** enables or disables the “Temperature Sensor” tab in the tree on the left. See section 2.2.2 for details.
- **Screensaver:** enables or disables the “Screensaver” tab in the tree on the left. See section 2.2.3 for details.

- **LEDs and Display config.:** sets whether the LEDs and display should make use of the pre-defined brightness levels ("Default") or of a user-defined configuration ("Custom").
 - "Default": the LEDs will remain off while in the "off" state, and at the maximum light level while in the "on" state. The display contrast level is set to 7.
 - "Custom": a specific tab will be included in the tab tree on the left so the integrator can set the desired light levels for the "off" and "on" states and whether to use the Night Mode or not. The display contrast level will also be configurable.

See section 2.2.4 for details.

- **Sounds:** sets whether the sound functions (button beeps, alarm and doorbell) should work according to the pre-defined configuration ("Default") or to a user-defined configuration ("Custom"). See section 2.2.5 for details.
- **Advanced configuration:** enables or disables the "Advanced" tab in the tree on the left. See section 2.2.6 for details.

The project topology shows the following objects by default:

- **[General] Time of day:** object for updating the time shown on the display.

Important: *the time of day must be set through the bus by means of an external reference. Note that in the absence of power, the clock will get outdated.*
- **[General] Scene: Receive** and **[General] Scene: Send:** objects for respectively receiving and sending scene values from/to the KNX bus whenever it is necessary (e.g., when the user touches a button that has been configured to send scene commands; see section 2.3.3 and section 2.3.4).

2.2.2 TEMPERATURE SENSOR

TMD-Display is equipped with **one internal temperature probe** which can monitor the ambient temperature of the room, thus making the device capable of reporting it to the KNX bus and of triggering certain actions when the temperature reaches specific values.

Please refer to the specific manual “**Temperature Sensor in TMD-Display One**” (available at the Zennio homepage, www.zennio.com) for detailed information about the functionality and the configuration of the related parameters.

2.2.3 SCREENSAVER

The screensaver is a special page that will only be shown after a period of inactivity, configurable by parameter.

It is possible to configure the screensaver to only show the current **Time**, the current **Temperature** (selecting the desired measurement source: the internal temperature sensor or an external value) or **both** (alternating every five seconds).

Notes:

- *The temperature shown will be truncated to the range [-99°C, 199°C].*
- *The time of day must be set through the bus by an external reference.
Note that in the absence of power the clock will get outdated.*

The screensaver disappears when any button is touched. It can be set by parameter whether, while the screensaver is active, this press should simply cause the screensaver interruption or, moreover –apart from hiding the screensaver–, the execution of the action corresponding to the pressed button.

ETS PARAMETERISATION

This screen is divided into three parts: Activation, Content and Exit, containing the following parameters:

- **Activation timeout:** time to automatically show the screensaver after the last button touch. Range: 1 – 255 seconds, minutes or hours.
- **Time of Day:** sets whether to show the current time or not.

- **Temperature:** sets whether to show the current temperature or not. When enabled, the following parameter will show up:
 - **Taken from:** defines the source of the temperature value: “Internal sensor” or “External reference”. The latter will bring a new two-byte object to the project topology (“**[General] Screensaver - External temperature**”) so that it the device can receive the required values from the bus.
- **Run button action on screensaver exit:** sets whether touching a button while the screensaver is active should cause the execution of the button action, apart from hiding the screensaver.

Figure 6 General – Screensaver.

2.2.4 LEDs & DISPLAY

As anticipated in section 2.2, the integrator can configure the **LEDs of the buttons** to make use of the pre-defined brightness levels or of user-defined levels.

To begin with, each LED can commute between two states: **off** (which not necessarily means “no light”) and **on** (which not necessarily means “light on”). They will switch their states according to the options explained in ANNEX I: LED Illumination Modes.

Moreover, the LEDs and the display can also commute between two operation modes: the **normal mode** and the **night mode**. The second one is optional. It is provided for temporary situations and environments where an excess of brightness may disturb the user. In such cases, it will be possible to switch the mode by means of a one-bit object and/or a scene object.

Note: a general parameter is provided to make the ETS parameterisation easier in case the night mode is not required and the integrator feels comfortable with the default on/off brightness levels.

Regarding the display, it is possible to parameterise a contrast level in parameters. The integrator can also enable an object to change the display contrast in real time.

ETS PARAMETERISATION

The screenshot shows the 'LEDs & Display' configuration window. On the left is a tree view with 'GENERAL CONFIGURATION' expanded, showing 'LEDs & Display' selected. The main area is divided into two sections: 'Normal Mode' and 'Night Mode'. In 'Normal Mode', there are three input fields: 'LEDs: OFF level brightness' (value 0), 'LEDs: ON level brightness' (value 255), and 'Display: Brightness' (value 10). Each has a checkbox and a numeric input field with up/down arrows. The 'Night Mode' section has a checkbox that is currently unchecked. Below this, there is a 'Display contrast level' input field (value 7) and an 'Object for changing the contrast level' checkbox, both with up/down arrows.

Figure 7 General – LEDs & Display config.

After selecting “Custom” for “**LEDs and Display config.**” (see section 2.2.1), a new tab will be incorporated into the tree on the left.

The parameters shown in Figure 7 are equivalent to those for the “Default” configuration of parameter “**LEDs and Display config.**”.

The upper section of this new screen is for the LED brightness configuration while the lower is for the display brightness configuration.

LED Brightness Levels

● Normal Mode:

- **LEDs: OFF level brightness:** values between 0 (default) and 255.
- **LEDs: ON level brightness:** values between 0 and 255 (default).
- **Display: Brightness:** values between 0 and 10 (default).

- **Night Mode:** in case of being this mode necessary, this checkbox needs to be marked, which will incorporate some new parameters:

- **LEDs: OFF level brightness:** values between 0 and 255 (1 by default).
- **LEDs: ON level brightness:** values between 0 and 255 (8 by default).
- **Display: Brightness:** values between 0 and 10 (default).

The screenshot shows the 'LEDs & Display' configuration page. On the left is a sidebar with 'GENERAL' expanded, containing 'CONFIGURATION', 'LEDs & Display' (selected), 'BUTTONS', and 'DISPLAY'. The main area is divided into 'Normal Mode' and 'Night Mode' sections, each with a checkbox and three input fields for brightness. Below these is a 'Brightness Mode Control' section with checkboxes for 'Control object: 1-bit' and 'Control object: Scene', a 'Value' dropdown, and a 'Brightness Mode after ETS download' dropdown. At the bottom, there is a checkbox for 'Light up when any button is pressed' and a 'Length of lighting' input field with a unit multiplier.

Mode	LEDs: OFF level brightness	LEDs: ON level brightness	Display: Brightness
Normal Mode	0	255	10
Night Mode	1	8	10

Brightness Mode Control:

- ☒ Control object: 1-bit
 - Value: 0 = Normal; 1 = Night
- ☐ Control object: Scene
- Brightness Mode after ETS download: Normal
- ☒ Light up when any button is pressed
- Length of lighting: 10 x 1 s.

Figure 8 General – LEDs & Display – LED Brightness.

In case of enabling the night mode, some more options can be configured:

- **Control object: 1 bit:** when marked, it will be possible to switch the mode by writing to a binary object (“**[General] LEDs & Disp - Brightness Mode**”). A specific drop-down list will show up to select which value should trigger which mode (“0 = Normal; 1 = Night” or “0 = Night; 1 = Normal”).
- **Control object: Scene:** when marked, it will be possible to switch the mode by writing a certain scene value to “**[General] Scene: Receive**”. Two specific textboxes will show up to enter what scenes (1 through 64) will trigger each mode.
- **Idle time to change to Night Mode (0=disabled):** when the time set in this parameter elapses, TMD-Display One will switch to Night Mode (provided that it was not already in this mode). The range is 0 to 65535 seconds (0 by default).

- **Brightness Mode after ETS download:** sets which of the two modes (“Normal” or “Night”) will be active after an ETS Download.

Once either **Control object: 1-bit** or **Control object: scene** have been activated, a new parameter will be shown to allow a temporary transition to normal mode when a button is pressed during the night mode:

- **Light up when any button is pressed:** sets whether pressing on one of the enabled buttons during the night mode should imply a temporary transition to normal mode or not.
- **Length of lighting:** sets the time (1 to 65535 seconds) the device will remain in normal mode before switching back to night mode. The default value is 10 seconds.

Display




Figure 9 General – LEDs & Display – Display configuration.

- **Display contrast level:** value to set the display contrast level, from 1 to 10 (7 by default).
- **Object for changing the contrast level:** enables a one-byte object (“[General] Display - Contrast”) to change the display contrast level in real time.

2.2.5 SOUNDS

Apart from the behaviour of the LEDs, it is possible to make TMD-Display emit a **brief beep** as an acoustic feedback in two situations:

- **When a button is pressed:** short beep indicating that the user has pressed a button. This only applies to step controls, i.e., controls that walk through a certain range of values and that do not send a value after every touch, but only the final value after the last press.

- **When an action has been triggered:** sharper beep than the above one, indicating that a value is being sent to the KNX bus.

Enabling and disabling the button sounds can be done in parameters or through an object, being also possible to define in parameters whether the button sounds should be initially enabled or not.

On the other hand, TMD-Display can also emit the following sounds on request (through the corresponding communication objects):

- **Doorbell sounds** (a single beep),
- **Alarm sounds** (a sequence of brief beeps with a higher pitch),


The alarm sequence will only stop when the alarm object gets deactivated or when the user touches any of the buttons (this will not trigger any action, only the alarm deactivation). Note that doorbell requests are ignored while the alarm is active.

A general parameter is provided to make the ETS parameterisation easier in case the doorbell and alarm functions are not required and the user feels comfortable with the default button beeps. On the contrary, customising the button, doorbell and alarm sounds involves a set of parameters, as explained next.

ETS PARAMETERISATION

In case the default button beep sound matches the requirements of the installation and the doorbell and alarm functions are not necessary, the “**Sounds**” parameter in the general **Configuration** tab (see section 2.2.1) can be set to “Default”. This will also imply that the button beeps will be unconditional, as it will not be possible to disable this function through an object.

On the other hand, if set to “Custom”, a specific tab named “**Sounds**” will show up in the tab tree on the left. The initial configuration of this screen is equivalent to the aforementioned default option. However, the following parameters will be configurable.



Disable button sound	<input type="checkbox"/>
Enable / Disable button sound through a 1-bit object	<input checked="" type="checkbox"/>
Value	0 = Disable; 1 = Enable
Status after ETS Download	Enabled
Object for doorbell	<input type="checkbox"/>
Object for alarm bell	<input type="checkbox"/>

Figure 10 General – Sounds.

- **Disable button sound:** enables or disables the button and action beeps. If enabled (default option) the following parameters will also be available:
 - **Enable / Disable button sounds through a 1-bit object:** makes it possible to disable / resume the button beeping function in runtime by writing to a specific object (“**[General] Sounds – Disabling button sound**”).

The values (0 or 1) that will disable / resume it are parameterisable through “**Value**”.
 - **Button sound after ETS Download:** sets whether the button beeping function should start up enabled (default option) or disabled after an ETS download. This makes sense if the “**Enable/Disable Button Sounds Using 1-Bit Object**” checkbox (see below) is enabled too.
- **Object for doorbell:** enables or disables the doorbell function. If enabled, a specific object (“**[General] Sounds: Doorbell**”) will be included into the project topology. The value that will trigger the sound (1 or 0) must be set in “**Value**”.
- **Object for alarm bell:** enables or disables the alarm function. If enabled, a specific object (“**[General] Sounds: Alarm**”) will be included into the project topology. The values (1 or 0) that will trigger the alarm sequence and then stop it must be entered in “**Value**”.

2.2.6 ADVANCED

As stated in section 2.2.1, an independent tab for the parameterisation of some advanced functions is shown in ETS if enabled from the “Configuration” tab.

These functions are explained next.

ETS PARAMETERISATION

The “Advanced” tab contains the following parameters:




Figure 11 General - Advanced.

- **Translations:** enables or disables the “Translations” tab in the tree on the left. See section 2.2.7 for details.
- **Touch locking:** enables or disables the “Touch locking” tab in the tree on the left. See section 2.2.8 for details.
- **Cleaning function:** enables or disables the “Cleaning function” tab in the tree on the left. See section 2.2.9 for details.
- **Welcome greeting on the display:** enables or disables the “Welcome greeting” tab in the tree on the left. See section 2.2.10 for details.
- **Welcome back object:** enables or disables the “Welcome back” tab in the tree on the left. See section 2.2.11 for details.
- **Central touch area:** enables or disables the “Central area” tab in the tree on the left. See section 2.2.12 for details.

- **Hide explanation texts:** displays or hides the explanation texts on the top of the parameter screen of some functions. Experienced users may prefer to hide these texts to have simpler parameter screens.
- **Hide INFO parameters:** displays or hides the INFO textboxes on the top of the parameter screen of each control. These textboxes have no functionality – they are offered for the convenience of the integrator, as they allow assigning a description to each control, which may be useful in case of later re-parameterisation of the project.



Figure 12 “Info” Textboxes.

2.2.7 TRANSLATIONS

The labels shown by the boxes on the screen, as well as the texts of the enumerated controls, can be translated into up to five different languages. Switching from one language to another can be done through three types of communication objects:

- **Up to five one-bit objects**, one for each language. When receiving a “1” through one of them, the corresponding language is activated, if enabled (otherwise the main language is activated).
- **A one-byte scene object**. The values expected by this object are fixed from 0 to 4, to select the corresponding language. When receiving the value of a non-enabled language, the main language will be activated. When the received value is out of range, the active language remains unchanged.
- **A two-byte ASCII object**. The values expected by this object are two ASCII code characters corresponding to the ISO 639-1 standard. When receiving the value of a non-enabled language, the main language is selected.

Note: please refer to http://en.wikipedia.org/wiki/List_of_ISO_639-1_codes for a table with the language codes.

ETS PARAMETERISATION

After enabling “**Translations**” in the “Advanced” configuration screen (see section 2.2.6), a new tab will be incorporated into the tree on the left.




Figure 13 General – Translations.

This screen contains the following parameters:

- **Main language:** read-only parameter to make it evident that the main language is always enabled.
 - **Select language:** list of the available languages.
- **Language X:** enables or disables the additional language X.
 - **Select language:** list of available languages to select the language X.

Only the Main language is enabled by default.

While Translations stays enabled, the following objects are visible:

- “[General] Translations – Select language” (one-byte).
- “[General] Translations – Main language” (one-bit).
- “[General] Translations – Select language” (two-byte).

Up to four specific objects for the additional languages will be also shown, if required:

- “[General] Translations – Language X” (one bit).

These objects work accordingly to the behaviour mentioned above.

2.2.8 TOUCH LOCKING

The touch panel of TMD-Display can be optionally locked and unlocked anytime by writing a configurable one-bit value to a specific object provided for this purpose. It can also be done through scene values.

While locked, user presses on the touch buttons will be ignored: no actions will be performed (and no LEDs will change their states) when the user presses on any of the controls. However, if configured, a message will be shown on the display for three seconds if the user touches a button during the lock state.

ETS PARAMETERISATION

After enabling “**Touch Locking**” (see section 2.2.6), a new tab will be incorporated into the tree on the left.




Figure 14 General - Touch Locking.

This screen is divided into two parts: Control and Indication.

Control comprises two simple, non-exclusive checkboxes to select how the touch panel lock/unlock should be performed:




Figure 15 General - Touch Locking: Control.

- Upon the reception of a one-bit value ("**1 bit object**").

When marked, a specific drop-down list will show up to select which value should trigger which action ("0 = Unlock; 1 = Lock" or "0 = Lock; 1 = Unlock"). These values are to be received through object "[**General**] **Lock Touch**".


- Upon the reception of a scene value ("**Scene object**").

When marked, two specific textboxes will show up to enter the scene numbers (1 - 64) that should trigger each action. These values are to be received through the general "[**General**] **Scene: Receive**" object.

Indication comprises a parameter to select how to show the lock status:

- **How to show lock status?** Sets whether to display a message on the screen when the device is locked and the user attempts to touch a button ("Display message") or not ("Do nothing").

When the first one is selected, one **Message** textbox appears per enabled language (see section 2.2.7) to enter the desired message.



INDICATION	
How to show lock status?	Display message
Message	Locked

Figure 16 General - Touch Locking – Indication.

2.2.9 CLEANING FUNCTION

This feature is very similar to the touch locking, that is, it locks the touch area, thus discarding further button touches. The difference is that this function remains active only during a parameterisable time, and then stops.

This function is intended to let the user clean the touch area with the certainty of not triggering unwanted actions.

A message can be shown during the cleaning state. When the timeout is about to end, it is also possible to make this message blink or to make the device beep (or both).

ETS PARAMETERISATION

After enabling “**Cleaning function**” (see section 2.2.6) a new tab will be incorporated into the tree on the left.




Figure 17 General – Cleaning function.

This screen contains the following parameters:

- **Time to exit cleaning status:** timeout to deactivate the cleaning function, once triggered. Range: from 5 to 65535 seconds (15 by default).
- **How to show cleaning status:** sets whether to show a message during the cleaning state. The options are: “Do nothing” and “Display message”.

When the latter is selected the following parameters appear:

- **Message:** textbox to enter the desired message.
- **Notify expiration?:** sets whether to notify the timeout expiration or not. The options are: “No”, “Blink message”, “Play sound” and “Both”. When any of the three later options is selected, a new parameter shows up:
 - **Length of the warning:** sets the ahead-time (5 to 65535 seconds; 10 by default) to start the notification prior to the end of the cleaning function.

The “[**General**] **Cleaning Function**” one-bit object triggers the cleaning function when it receives a “1” from the KNX bus.

2.2.10 WELCOME GREETING

This function permits showing the user a welcome message of up to four lines of text on the display, each of which can be object-dependant or set in parameters.

When a “1” is received through the welcome greeting one-bit object, the display will become blank and show the welcome text. The same will happen if any of the 14-byte objects that define the text lines receives a new value from the bus.

It is also possible to make the button LEDs flash during the welcome state.

ETS PARAMETERISATION

After enabling “**Welcome greeting**” (section 2.2.6), a new tab will be incorporated into the tab tree. A one-bit object named “[**General**] **Welcome Greeting**” will also be shown in the project topology, to trigger the welcome message by sending the value “1”.

When welcome greeting object is set to '1' or any of the welcome greeting text objects is received, the display shows the text lines until any button is touched

Line	Source	Text
Line 1	Fixed	Welcome Mr./Mrs.
Line 2	Received from text Object	Received from text Object
Line 3	Fixed	Touch any button
Line 4	Fixed	

LEDs flashing during welcome status? ☐

Figure 18 General – Welcome Greeting.

This screen contains the following parameters:

- **Line X**: sets whether the corresponding text line will be pre-defined (“Fixed”) or object-dependent (“Received form text object”).

If “Fixed” is selected, the following parameter will appear:

- **Text**: sets the desired text for the corresponding line.

The 14-byte object “[General] Welcome Greeting – Line X” will be shown up to four times, depending on how many text lines have been assigned the option “Received from text object”.

- **LEDs Flashing during Welcome Status?**: sets whether the LEDs of the buttons should blink or not during the welcome greeting.

With a parameterisation as the one shown in , if “Mr. Marshall” is received through the “[General] Welcome Greeting – Line 2” object, the display will show the following message:



Figure 19 Welcome greeting message example.

2.2.11 WELCOME BACK OBJECT

TMD-Display can send a specific object (the *welcome back object*) to the KNX bus when the user presses a touch button after a significant amount of time since the last press. Sending it or not can also depend on an **additional, configurable condition** consisting in the evaluation of up to five binary objects.

Any actions that in normal operation may be executed will not be if the welcome back object is sent to the bus. Thus, if the user presses a button and this causes the welcome back object to be sent, the normal action of that button will not be triggered. On the other hand, if the additional condition is not evaluated to true, the device will react normally. Hence, the action corresponding to the button touch will be executed.

The welcome back object can consist in a **one-bit** value or a **scene** value (or both), depending on the parameterisation.

ETS PARAMETERISATION

After enabling “**Welcome Back Object**” (see section 2.2.6), a new tab will be incorporated into the tree on the left.

This screen contains the following parameters:

Figure 20 General - Welcome Back Object.

- **Timeout (since last touch):** sets the minimum time (1 to 255 seconds, 1 to 255 minutes, or 1 to 255 hours) that should elapse after the last button touch before the next one triggers the execution of the welcome back function.
- **Additional Condition:** sets if sending the welcome back object should also depend on an external condition. The option by default is “No Additional Condition”. The following are available too:
 - Do not send unless all additional conditions are 0: the welcome back object will only be sent if all the condition objects are found to have the value “0”.
 - Do not send unless all additional conditions are 1: the welcome back object will only be sent if all the condition objects are found to have the value “1”.
 - Do not send unless at least one of the additional conditions is 0: the welcome back object will only be sent if at least one of the condition objects is found to have the value “0”.

- Do not send unless at least one of the additional conditions is 1: the welcome back object will only be sent if at least one of the condition objects is found to have the value “1”.
- **Welcome Back Object (1 Bit)**: checkbox to enable the sending of a 1-bit value (through “[General] Welcome back”) when the welcome back function is triggered and the condition (if any) evaluates to true. The desired value (0 or 1) should to be set in “Value”.
- **Welcome Back Object (Scene)**: checkbox to enable the sending of a scene run request (through “[General] Scene: send”) when the welcome back function is triggered and the condition (if any) evaluates to true. The desired scene number (1 through 64) should to be entered in “Value”.

Figure 21 General - Welcome Back Object - Custom Configuration.

2.2.12 CENTRAL AREA

When enabling this feature, TMD-Display One will also recognise user touches in the centre of the touch panel, that is, the area between the two button columns.

One-bit or scene values can be sent to the bus when the user touches this area.

ETS PARAMETERISATION

After enabling “**Central touch area**” (see section 2.2.6), a new tab will be incorporated into the tree on the left.




Figure 22 General – Central area.

This screen contains the following parameters:

- **Type of object to send when central area is touched:** sets the object type that will be sent when the central area is pressed. The options are:
 - “None”,
 - “1 bit object”: adds the 1-bit object “[General] Central area” to the project. When the central area is touched, this object will be sent with the value set in **Action** (the options are “Send 1”, “Send 0” and “Toggle 0/1”).
 - “Scene object”: when the central area is touched, TMD-Display will send the “[General] Scene: send” object with the value set in **Scene number** (1 to 64), decremented by one according to the KNX standard.

2.3 BUTTONS

2.3.1 CONFIGURATION

TMD-Display features **eight capacitive buttons** at the user's disposal for the execution of actions. Each will perform a specific function at any time, as their functions do not depend on alternating menus, pages, etc.




Figure 23 Touch panel

As Figure 23 Touch panel shows, three areas can be distinguished in the front panel:

- **The buttons**, grouped in pairs.
- **The display**, at the top of the front panel.
- **The central touch area**, between the two button columns.

All the buttons are identical; this brings a high level of versatility for a wide variety of applications. The following is a list of the functions that can be assigned to each pair of buttons.

- **Disabled** (none of the two buttons will react to user presses).
- **Pair Buttons** (the two buttons will work jointly):
 - Switch (binary).
 - Two Objects (Short Press / Long Press).
 - Light dimmer.
 - Shutter.
 - Scaling.

- Counter.
- Enumeration.
- Float.
- [Climate] Temperature setpoint.
- [Climate] Mode.
- [Climate] Fan.

● **Individual Buttons** (each button in the pair will work independently):

- Disabled.
- Binary.
- Hold & Release.
- Two Objects (short press / long press).
- Scene.
- Scaling constant.
- Counter constant.
- Float constant.
- Light dimmer.
- Shutter.
- Enumeration.
- [Climate] Fan.

Apart from the button function itself, the integrator can select the desired behaviour of the button **LEDs**. The different **illumination modes** have been detailed in [ANNEX I: LED Illumination Modes](#).

The following sections will detail the involved configuration.

ETS PARAMETERISATION




Figure 24 Buttons - Configuration.

As stated in section 2.1, an independent tab for the parameterisation of the buttons is shown in ETS by default, initially containing only a sub-tab named Configuration.

One drop-down list with the following options is shown per pair of buttons.

- Disabled. See section 2.3.2.
- Pair. Selecting this option brings a new tab to the tree on the left (named “Pair X”, where X depends on the button pair). See section 2.3.3.
- Individual. Selecting this brings the checkboxes “**Button X1**” and “**Button X2**” (where X depends on the button pair), which allow making each of the two buttons functional or not. Depending on this, up to two new tabs (named “**Button Xn**”) will be included in the tree on the left. See section 2.3.4.

Note: if a button pair is set to “Individual” but the “Button Xn” checkbox is left unmarked, that button will behave as if the pair had been set to “Disabled”.

The following parameters apply to all pairs:

- **Action of the pair buttons:** sets how the two-button controls should behave:
 - Left = Off/Down/Decrement; Right = On/Up/Increment,
 - Right = Off/Down/Decrement; Left = On/Up/Increment,
 - Every button pair is configured separately, which will incorporate an additional parameter to the configuration window of each pair control to

allow defining the action of each of the two buttons (unless the function of the control has been set to “Enumeration” or “[Climate] Mode”).

- **LED Illumination Control (All Buttons):** sets how the LED indicators of all the touch buttons should behave. The available options are (see [ANNEX I: LED Illumination Modes](#) for details):

- Regular,
- State-Dependent (where available),
- State-Dependent (where available) (both LEDs),
- Dedicated Object,
- Configure every button (pair) separately.

In case of selecting “Configure every button (pair) separately”, there will be a specific parameter in every control for specifically selecting the desired behaviour of the LED (or LEDs), unless it is configured as “Enumeration” or “[Climate] Mode”.

2.3.2 DISABLED

While a button pair stays disabled, none of the two buttons will be functional: touching them will not cause the execution of actions, nor will make the associated LED light.

ETS PARAMETERISATION

This function has no related parameters.

2.3.3 PAIR

Pair buttons configured to work jointly can be assigned the following control functions:

- **Switch:** pressing one of the two buttons will make TMD-Display send a binary value to the bus, while pressing on the other will make it send the inverse binary value. It is possible to configure which one does what.

Under a “**state-dependent**” LED illumination (see [ANNEX I: LED Illumination Modes](#)), the LED of the corresponding button will remain on/off according to the current state (on/off) of the switch. On the other hand, under a “**state-dependent (both LEDs)**” LED illumination, both of them will remain on while the switch is in the “on” state, and off while in the “off” state.

- **Two Objects (Short Press / Long Press):** permits sending specific binary values both after a short or a long press on any of the two buttons (i.e., they will work as a joint control; for independent buttons, please configure them as individual). Different objects will be used for the short and long presses.

Moreover, it is possible (in parameters) to make the “**state-dependent**” and “**state-dependent (both LEDs)**” LED illumination modes (see [ANNEX I: LED Illumination Modes](#)) depend on either one object or the other. However, if “**LED Illumination Control (All Buttons)**” (section 2.3.1) has been set to “state-dependent (where available)” only the short press object will be considered

- **Dimmer:** short-pressing one of the two buttons will make TMD-Display send a switch-on order to the bus, while doing so on the other button will make it send a switch-off order.

Long presses will make it send a step dimming order (the value of which is configurable) to make a dimmer increase or decrease the light level (and a stop order as soon as the user releases the push button). It is possible to configure which button does what.

Under a “**state-dependent**” LED illumination (see [ANNEX I: LED Illumination Modes](#)), the LED of the corresponding button will remain on/off according to whether the current value of the light level status object (which should be updated by the actual dimmer) is greater than 0% or not. On the other hand,

under a **“state-dependent (both LEDs)”** LED illumination, both LEDs together will remain on or off depending on such value.

- **Shutter:** this option permits making use of the two buttons to control a shutter actuator connected to the bus. Two alternative control methods are possible:
 - Standard: a long press will make the device send to the KNX bus an order to start moving the shutter (upwards or downwards, depending on the button), while a short press will make it send a stop order (which will be interpreted as an order to step up or to step down –depending on the button– if the shutter was not in motion and such function is available).
 - Hold & Release: as soon as the button is held, the device will send the KNX bus an order to start moving the shutter (upwards or downwards, depending on the button). Once the button is released, it will send an order to stop the shutter.

The **“state-dependent”** and **“state-dependent (both LEDs)”** LED illumination modes are not available for this function (only the **“regular”** and **“dedicated object”** LED illumination are available). See ANNEX I: LED Illumination Modes for details.

- **Scaling, Counter and Float:** user touches over the buttons will trigger the sending of a certain numerical value to the bus (this value will be progressively increased or decreased every time the user touches one button or the other) through the control object.

These controls provide a parameter to **link them to a box in the display** so the current numerical value is shown on the display. The screen will reflect the new values as the user touches the buttons, however values are actually sent to the bus 1.5 seconds after the last press.

The **“state-dependent”** and **“state-dependent (both LEDs)”** LED illumination modes are not available for this function (only the **“regular”** and **“dedicated object”** LED illumination are available). See ANNEX I: LED Illumination Modes for details.

- **Enumeration:** pressing the buttons will make TMD-Display send a one-byte (unsigned) value to the bus. It is possible to distinguish up to 6 different

values. Successively pressing on the buttons will make TMD-Display walk through the different values.

As the above functions, this type of control provides parameter to **link the control with a box in the display** in order to show the current value on the display. Again, values are sent to the bus 1.5 seconds after the last press.

The “**state-dependent**” and “**state-dependent (both LEDs)**” LED illumination modes are not available for this function (only the “**regular**” and “**dedicated object**” LED illumination are available). See ANNEX I: LED Illumination Modes for details.

- **[Climate] Temperature setpoint:** permits controlling the temperature setpoint of an external thermostat by means of a button pair and the display.

This function can also be **linked to a box in the display** in order to show the current setpoint value. The box will reflect the value (in °C) of the status object, which gets automatically updated after sending control orders (that is, after pressing the buttons), being even possible to receive values from the bus, for example, from the corresponding setpoint status object from the external thermostat.

The “**state-dependent**” and “**state-dependent (both LEDs)**” LED illumination modes are not available for this function (only the “**regular**” and “**dedicated object**” LED illumination are available). See ANNEX I: LED Illumination Modes for details.

- **[Climate] Mode:** pressing one of the two buttons will make TMD-Display send climate mode values to the bus. Two mode control types are possible: **Heat / Cool** and **Extended** (HVAC).

As above, it is possible to **link the control to a box in the display** in order to show the current mode on it.

The “**state-dependent**” and “**state-dependent (both LEDs)**” LED illumination modes are not available for the Extended mode (only the “**regular**” and “**dedicated object**” LED illumination are available). For the Heat / Cool mode all the illumination options are available. See ANNEX I: LED Illumination Modes for details.

- **[Climate] Fan:** pressing one of the two buttons will make TMD-Display One send a binary value to the bus that allows changing the fan speed (up to **five levels** available). This value can be either binary (increase / decrease orders), scaling (0% - 100%) or enumerated.

Furthermore, it is possible to configure the **speed 0** as an additional fan level, and/or another level to activate the **Auto mode**.

The order to activate the auto mode can be sent over a one-bit object, independent from the fan control object, or alternatively consist in the speed level 0. In the latter case, level 0 will imply triggering the Auto mode.

The three available control types are:

- **“1 bit (decrease/increase)”**: one-bit values (increase or decrease) will be sent according to the action configured for each button.

In this case, switching from the current fan level to a non-consecutive level involves going through each of the intermediate levels.

- **“Scaling”**: button presses will make the device send percentage values through the corresponding one-byte object.

Every press will activate the subsequent (or preceding) fan level, depending on the current one. Therefore, the percentage values sent will depend on the number of the available levels and on whether the Auto mode and the speed level 0 are available or not.

- **“Enumeration”**: this control is similar to the one above, although integer values are sent instead of scaling values.

% Values based on fan levels						
Speed Levels		1	2	3	4	5
Enumeration value	1	100	50,2	33,3	25,1	20
	2	-	100	66,7	50,2	40
	3	-	-	100	75,3	60
	4	-	-	-	100	80
	5	-	-	-	-	100

Table 1 Fan levels.

Table 1 shows the relation between the scaling values and the enumeration values, depending on the number of speed levels configured (note that if the Auto mode or the speed level 0 are allowed one more level is added, corresponding to value 0).

For the scaling and enumeration controls, the object is sent to the bus slightly delayed, once the desired value has been set by the user. It is advisable to **link the control with a box in the display** in order to show the current value on the display.

Under a “**state-dependent**” LED illumination, the LED of the corresponding button will remain on/off according to the current state of the fan. On the other hand, under a “**state-dependent (both LEDs)**” LED illumination, both of them will remain on or off while the fan level is greater than 0 or not, respectively. The “**regular**” and “**dedicated object**” LED illumination modes are also available. See [ANNEX I: LED Illumination Modes](#) for details.

ETS PARAMETERISATION

When a button pair has been configured to work as a joint control, a specific tab (“**Pair X**”) becomes available under “Buttons” in the tree on the left.




Figure 25 Buttons - Pair A.

Note: the *INFO* textboxes are functionless (they simply bring the option to add a description to each button of the project) and can be hidden if desired. See section 2.2.6.

The main parameter that needs to be configured is:

- **Function:** sets the desired function for the button pair: “Switch”, “Two objects (short press / long press)”, “Dimmer”, “Shutter”, “Scaling”, “Counter”, “Enumeration”, “Float”, “[Climate] Temperature Setpoint”, “[Climate] Mode” or “[Climate] Fan”.

Depending on the function, some more parameters are shown, as described next. Please note that in the next pages the general notation “[X]” is used for the name of the communication objects, as “X” depends on the button pair (A, B, etc.).

Switch

Function	Switch
Action	Left=0; Right=1
LED illumination control	State-dependent

Figure 26 Pair Buttons – Switch.

- **Action:** assigns each of the two buttons the value to be sent through “[Btn] [X] Switch” (which has the Write flag enabled, so the state of the switch can be updated from external devices). The options are “Left=0; Right=1” and “Left=1; Right=0”.

Note: *this parameter will remain hidden unless having selected “Every button pair is configured separately” in **Action of the pair buttons** (see section 2.3.1).*

- **LED illumination control:** sets the behaviour of the LEDs on the buttons. The options are “Regular”, “State-dependent”, “State-dependent (both LEDs)” and “Dedicated Object”.

In case of selecting the latter, the object “[Btn] [X] Led On/Off” will be included in the project topology and a new parameter to select the value to switch off and on the LED shows up:

LED illumination control	Dedicated Object
Value	0 = Off; 1 = On

Figure 27 LED illumination control - Dedicated object.

Note: *this parameter will remain hidden unless having selected “Configure every button (pair) separately” in “**LED Illumination Control (All Buttons)**” (see section 2.3.1).*

Two Objects (short Press / long press)

Function	Two objects (short press / long press)
Long press threshold time	5 ds
Action on short press	Left=0; Right=1
Action on long press	Left=0; Right=1
LED lighting	Dedicated Object
Value	0 = Off; 1 = On

Figure 28 Pair Buttons - Two Objects (Short Press / Long Press).

- **Long press threshold time:** sets the minimum time the user should hold the button in order to consider it a long press. The available range is 5 to 50 tenths of a second, being 5 tenths the default value.
- **Action on short press:** sets the value that will be sent through “[Btn] [X] Two switches - Short press” after the user short-presses one of the two buttons.

- “Left=0; Right=1”.
- “Left=1; Right=0”.

Note: *this parameter will remain hidden unless having selected “Every button pair is configured separately” in **Action of the pair buttons** (see section 2.3.1).*

- **Action on long press:** sets the value that will be sent through “[Btn] [X] Two switches: Long press” after the user long-presses one of the two buttons.

- “Left=0; Right=1”.
- “Left=1; Right=0”.

Note: *this parameter will remain hidden unless having selected “Every button pair is configured separately” in **Action of the pair buttons** (see section 2.3.1).*

- **LED illumination control:** analogous to the homonymous parameter for the Switch function (see above). In this case, however, selecting “State-

dependent" or "State-dependent (both LEDs)" brings an additional parameter, "**State Object**", to make the state of the LEDs correspond either to object "[Btn] [X] Two switches: Short press" ("Short Press Object") or to object "[Btn] [X] Two switches: Long press" ("Long Press Object").




Figure 29 Pair Buttons - Two objects (short press / long press) - LED illumination control.

Dimmer




Figure 30 Pair Buttons – Dimmer.

The switch orders will be sent through the "[Btn] [X] Light - On/Off" one-bit object, while the increase/decrease orders will be through the "[Btn] [PX] Light - Dimming" four-bit object.

On the other hand, the "[Btn] [X] Light Dimming (Status)" one-byte object may be linked to the light level status object of the dimmer (in fact, this object is only intended to receive values from the bus, not to send them). As explained in 2.3.3, the state-dependent LED lighting will be determined by the value of this object (LED off at 0% and on at any other level).

The parameters for this function are:

- **Step:** defines the dimming step ("100%", "50%", "25%", "12.5%", "6.25%", "3.1%" or "1.5%") to be sent to the light dimmer with every increase / decrease order.

Note: *since dimmers typically do not apply the new light level immediately (i.e., the step regulation is performed progressively) and since TMD-Display*

sends an order to interrupt the step dimming once the user releases the button, it is advisable to configure a step of 100%. This way, the user can perform any dimming step by simply leaving the button pressed and then releasing it without needing to make successive button presses.

- **Action:** assigns each of the two buttons the order to be sent:

- “Left=Off; Right=On”.
- “Left=On; Right=Off”.

Note: this parameter will remain hidden unless having selected “Every button pair is configured separately” in **Action of the pair buttons** (see section 2.3.1).

- **LED illumination control:** analogous to the homonymous parameter for the “Switch” and “Two Objects (short press / long press)” function (see above).

The percentage values will be sent to the bus through object “[Btn] [X] Scaling”.

Shutter

Function	Shutter
Type	Standard
Action	Left=Down; Right=Up
LED lighting	Regular

Figure 31 Pair Buttons – Shutter.

The move orders will be sent through “[Btn] [X] Shutter - Move”, while the stop orders will be sent through “[Btn] [X] Shutter Stop/Step” (for Standard type) or “[Btn] [X] Shutter - Stop” (for Hold & Release type).

The parameters for this function are:

- **Type:** sets the desired behaviour of the buttons, “Standard” or “Hold & Release” (the differences between them have been explained in previous pages).
- **Action:** assigns each of the two buttons the order to be sent:
 - “Left=Down; Right=Up”.

- “Left=Up; Right=Down”.

Note: *this parameter will remain hidden unless having selected “Every button pair is configured separately” in **Action of the pair buttons** (see section 2.3.1).*

- **LED illumination control:** analogous to the homonymous parameter for the previous functions (see above). In this case, the only options are “Regular” and “Dedicated Object”.

Scaling

Function	Scaling
Action	Left=Decrease; Right=Increase
Minimum Value	0 %
Maximum Value	100 %
Increment on short press	1 %
Increment on long press	10 %
Link the control with a box in the display	Box A
LED illumination control	Regular

Figure 32 Pair Buttons – Scaling.

- **Action:** assigns each of the two buttons the order to be sent:

- “Left=Decrease; Right=Increase”.
- “Left=Increase; Right=Decrease”.

Note: *this parameter will remain hidden unless having selected “Every button pair is configured separately” in **Action of the pair buttons** (see section 2.3.1).*

- **Minimum Value:** sets which value from the available range will be the minimum value permitted by the control. The available range is 0-100.
- **Maximum Value:** sets which value from the available range will be the maximum value permitted by the control after. The available range is 0-100.

- **Increment on Short Press:** sets the increase or decrease to be applied to the current value on every short press over the increase or decrease buttons, respectively (i.e., the smaller the increment, the more presses will be required). The available range is 0-100.
- **Increment on Long Press:** sets the increase or decrease to be applied to the current value on every long press over the increase or decrease buttons, respectively (i.e., the smaller the increment, the more presses will be required). The available range is 0-100.
- **Link the control with a box in the display:** sets the area of the display where to show the indicator of this control, i.e., the current numeric value. The selected box must be configured with the same data type (see section 2.4 for details).
- **LED illumination control:** analogous to the homonymous parameter for the previous functions (see above). In this case, the only options are “Regular” and “Dedicated Object”.

The percentage values will be sent to the bus through object “[Btn] [X] Scaling”.

Counter

Function	Counter
Action	Left=Decrease; Right=Increase
Size	1-byte
Signed?	<input type="checkbox"/>
Minimum Value	0
Maximum Value	255
Increment on short press	1
Increment on long press	10
Link the control with a box in the display	Box A
LED illumination control	Regular

Figure 33 Pair Buttons – Counter.

- **Action:** assigns each of the two buttons the order to be sent:

- “Left=Decrease; Right=Increase”.
- “Left=Increase; Right=Decrease”.

Note: *this parameter will remain hidden unless having selected “Every button pair is configured separately” in **Action of the pair buttons** (see section 2.3.1).*

- **Size:** sets the desired size of the object, “1 byte” or “2 bytes”.
- **Signed:** checkbox to set whether the object will be signed or unsigned.

The value ranges depend on the above two parameters:

- 1 byte unsigned: 0 – 255.
 - 1 byte signed: -128 – 127.
 - 2 bytes unsigned: 0 – 65535.
 - 2 bytes signed: -32768 – 32767.
- **Minimum Value:** sets which value from the available range will be the minimum value permitted by the control.
 - **Maximum Value:** sets which value from the available range will be the maximum value permitted by the control.
 - **Increment on Short Press:** sets the increase or decrease to be applied to the current value on every short press over the increase or decrease buttons, respectively (i.e., the smaller the increment, the more presses will be required).
 - **Increment on Long Press:** sets the increase or decrease to be applied to the current value on every long press over the increase or decrease buttons, respectively (i.e., the smaller the increment, the more presses will be required).

- **Link the control with a box in the display:** sets the area of the display where to show the indicator of this control, i.e., the current numeric value. See section 2.4 for details.
- **LED illumination control:** analogous to the homonymous parameter for the previous functions (see above). In this case, the only options are “Regular” and “Dedicated Object”.

The counter values will be sent to the bus through object “[Btn] [X] Counter - [size]”.

Enumeration

- **# Enums:** number of states (up to 6) that will be distinguished. For every distinguished state, one parameter named **Value j** will become available, in order to set the value sent through the communication object.
- **Value j:** numerical value (0 – 255) that will be sent through the control object when the user, after pressing the buttons, sets the control to state *j*. The actual sending will not be performed until 1.5 seconds after the last press.
- **Link the control with a box in the display:** sets the area of the display where to show the indicator of this control, i.e., the current numeric value. See section 2.4 for details.
- **LED illumination control:** analogous to the homonymous parameter for the previous functions (see above). In this case, the only options are “Regular” and “Dedicated Object”.

Function	Enumeration
# Enums	1
Value 1	0
Link the control with a box in the display	Box A
LED illumination control	Regular

Figure 34 Pair Buttons – Enumeration.

The values will be sent to the bus through object “[Btn] [X] Enumeration”.

Float

Function	Float
Action	Left=Decrease; Right=Increase
Minimum Value	-671088,625
Maximum Value	670760,9375
Increment on short press	0,5
Increment on long press	1
Link the control with a box in the display	Box A
LED illumination control	Regular

Figure 35 Pair Buttons – Float.

- **Action:** assigns each of the two buttons the order to be sent:

- “Left=Decrease; Right=Increase”.
- “Left=Increase; Right=Decrease”.

Note: *this parameter will remain hidden unless having selected “Every button pair is configured separately” in **Action of the pair buttons** (see section 2.3.1).*

- **Minimum Value:** sets which value from the available range (-671088.625 to 670760.9375) will be the minimum value permitted by the control.
- **Maximum Value:** sets which value from the available range (-671088.625 to 670760.9375) will be the maximum value permitted by the control.
- **Increment on Short Press:** sets the increase or decrease to be applied to the current value on every short press over the increase or decrease buttons, respectively (i.e., the smaller the increment, the more presses will be required). The available range is 0.1 – 670760.93750 (0.5 by default).
- **Increment on Long Press:** sets the increase or decrease to be applied to the current value on every long press over the increase or decrease buttons,

respectively (i.e., the smaller the increment, the more presses will be required). The available range is 0.1 – 670760.93750 (1 by default).

- **Link the control with a box in the display:** sets the area of the display where to show the indicator of this control, i.e., the current numeric value. The selected box must be configured with the same data type (see section 2.4 for details).
- **LED illumination control:** analogous to the homonymous parameter for the previous functions (see above). In this case, the only options are “Regular” and “Dedicated Object”.

The values will be sent to the bus through object “[Btn] [X] Float (2-bytes)”.

[Climate] Temperature Setpoint

Function	[Climate] Temperature setpoint
Minimum Value	10
Maximum Value	30
Action	Left=Decrease; Right=Increase
Link the control with a box in the display	Box A
LED illumination control	Regular

Figure 36 Pair Buttons – [Climate] Temperature Setpoint.

- **Action:** assigns each of the two buttons the order to be sent:

- “Left=Decrease; Right=Increase”.
- “Left=Increase; Right=Decrease”.

Note: *this parameter will remain hidden unless having selected “Every button pair is configured separately” in **Action of the pair buttons** (see section 2.3.1).*

- **Minimum Value:** sets which value from the available range (-671088.625 to 670760.9375; 10 by default) will be the minimum value permitted by the control.

- **Maximum Value:** sets which value from the available range (-671088.625 to 670760.9375; 30 by default) will be the maximum value permitted by the control after.
- **Link the control with a box in the display:** sets the area of the display where to show the indicator of this control, i.e., the current numeric value. The selected box must be configured with the same data type (see section 2.4 for details).
- **LED illumination control:** analogous to the homonymous parameter for the previous functions (see above). In this case, the only options are “Regular” and “Dedicated Object”.

The values are sent to the bus through “[Btn] [X] (Climate) Temperature setpoint”.

[Climate] Mode

Function	[Climate] Mode
Mode Type	Heat/Cool
Link the control with a box in the display	Box A
LED lighting	State-dependent

Figure 37 Pair Buttons – [Climate] Mode.

- **Mode Type:** sets mode control type: “Heat/Cool” or “Extended” (HVAC).
 - “Heat/Cool”: pressing one of the two buttons will make TMD-Display send a one-bit value to the bus (Left=Cool, value “0”; Right=Heat, value “1”).
 - “Extended”: pressing on the two buttons will make TMD-Display walk through the different HVAC modes and send a one-byte value to the bus according to the selected mode. Which of the modes should be available can be set through five specific checkboxes.

Mode Type	Extended
Auto	<input checked="" type="checkbox"/>
Heat	<input checked="" type="checkbox"/>
Cool	<input checked="" type="checkbox"/>
Fan	<input checked="" type="checkbox"/>
Dry	<input checked="" type="checkbox"/>

Figure 38 Pair Buttons – [Climate] Mode – Mode Type: Extended.

- **Link the control with a box in the display:** sets the area of the display where to show the indicator of this control, i.e., the current numeric value. The selected box must be configured with the same data type (see section 2.4 for details).

Note: this option is only available for *Extended mode type*.

- **LED illumination control:** sets the behaviour of the LEDs on the buttons. The options are “Regular”, “State-dependent”, “State-dependent (both LEDs)” and “Dedicated Object”.

The values will be sent to the bus through object “[Btn] [X] (Climate) Mode”.

[Climate] Fan

Function	[Climate] Fan
Control Type	1 bit (decrease/increase)
Speed Levels	3
Cyclical	<input checked="" type="checkbox"/>
Auto Mode	<input type="checkbox"/>
Allow Speed 0	<input type="checkbox"/>
Action	Left=Decrease; Right=Increase
LED illumination control	State-dependent

Figure 39 Pair Buttons – [Climate] Fan.

- **Control Type:** sets the type of the communication objects that will control the fan level.

- “1 bit (decrease/increase)”: orders of speed increase/decrease are sent through the one-bit object “[Btn] [X] Fan control (1 bit)”.
 - “Scaling”: scaling values are sent through the one-byte object “[Btn] [X] Fan control (scaling)”.
 - “Enumeration”: integer values are sent through the one-byte object “[Btn] [X] Fan control enumerated”.
- **Speed levels**: sets how many speed levels will be available in the control. 1 to 5 levels.
 - **Cyclical**: sets whether scrolling through the speed levels is circular or not. If checked, an increase order in the maximum level switches to the minimum and vice versa (in the minimum level a decrease order switches to the maximum).
 - **Auto Mode**: sets whether the fan Auto mode will be available or not. If checked, the following parameters are also shown.
 - **Dedicated Object for Auto Mode**: sets how the Auto mode should be activated. In the absence of a dedicated object, the Auto fan mode will be activated by switching to fan level 0.





Figure 40 Pair Buttons – [Climate] Fan – Auto Mode.

In this case the fan levels activated by short presses are:



On the other hand, marking the checkbox enables the one-bit object “[Btn] [X] Fan control – Auto mode”, which will trigger the Auto mode when it receives the value “1” (or “0”, depending on the subsequent parameter, “Value to Set the Auto Mode”).

Figure 41 Pair Buttons – [Climate] Fan – Dedicated Object for Auto Mode.

However, two alternative (and mutually exclusive) methods are possible to activate this mode:

- By short press: the Auto mode can be reached as a further level above the maximum one. In this case the fan levels activated by short presses are (note that **speed 0 is optional**):

(0)	Minimum	Medium	Maximum	Auto Mode
-------	---------	--------	---------	-----------

- By long press on any of the buttons of the control (requires checking **Long Press to Activate Auto Mode**).

A further long press deactivates back the Auto mode and resumes the previous fan level. Instead, a short press deactivates the Auto mode and switches to the next level (or previous, depending on the button). In this case the fan levels reachable through short presses are (**speed 0 is optional**):

(0)	Minimum	Medium	Maximum
-------	---------	--------	---------

(Here, the Auto mode is only activated by long press).

- **Allow speed 0**: sets whether the speed level 0 will be present or not. When the **Auto Mode without a dedicated object** has been configured, this option will be necessarily activated.
- **Action**: assigns each of the two buttons the order to be sent:
 - “Left=0; Right=1”.
 - “Left=1; Right=0”.

Note: *this parameter will remain hidden unless having selected “Every button pair is configured separately” in **Action of the pair buttons** (see section 2.3.1).*

- **Link the control with a box in the display:** sets the area of the display where to show the indicator of this control, i.e., the current fan speed. The selected box must be configured with the same data type (see section 2.4 for details).

Note: *this parameter is only available for the Scaling control type.*

- **LED illumination control:** analogous to the homonymous parameter for the previous functions (see above). The options are “Regular”, “State-dependent”, “State-dependent (both LEDs)” and “Dedicated Object”.

2.3.4 INDIVIDUAL

Buttons configured to work as individual (separate) controls can be assigned any of the following control functions from the corresponding **Button Xn** tab:

- **LED indicator:** user presses will not trigger any function although the LED will turn on or off depending on the values received from the bus.
- **Switch:** whenever the user touches the button, a binary value will be sent to the KNX bus. This value is configurable and may be 0 or 1, or alternate with every touch according to the sequence 1 → 0 → 1 → ...

Under a “**state-dependent**” LED illumination, the LED will remain on/off according to the current state (on/off) of the object.

- **Hold & Release:** as soon as the user touches the button, a binary value (“0” or “1”, configurable) will be sent to the KNX bus. And as long as the user releases the button, another value (“0” or “1”, also configurable) will be sent through the same object.

The “**state-dependent**” LED illumination mode is not available for this function.

- **Two Objects (Short Press / Long Press):** specific binary values will be sent both after a short or a long press (a different object will be used in each

case). Under a “**state-dependent**” LED illumination, the LED will remain on/off according to the current state (on/off) of either one object or the other, which can be configured in parameters. However, if “**LED Illumination Control (All Buttons)**” (see section 2.3.1) has been set to “state-dependent (where available)”, only the short press object will apply.

- **Scene:** after the user touches the button, an order to run a specific scene (configurable) will be sent to the bus. If enabled in parameters, orders to save the scene can also be sent to the bus after a three-second press on the button. The “**state-dependent**” LED mode is not available for this function.
- **Scaling Constant:** sends a percentage value (configurable) to the bus when the user touches the button. Under a “**state-dependent**” LED illumination, the LED will remain on/off depending on whether the current value of the object matches the one parameterised. This object can also be written from the bus, which will update the LED according to the new value.
- **Counter Constant:** sends an integer value (configurable) to the bus when the user touches the button. This value can be one-byte or two-byte sized, as well as signed or unsigned. The available ranges are shown next.

	1-byte	2-byte
Unsigned	0 – 255.	0 – 65535
Signed	-128 – 127.	-32768 – 32768.

Table 2 Counter Constant values

The “**state-dependent**” LED illumination mode is analogous as for the Scaling Constant function.

- **Float Constant:** sends a two-byte floating point value (configurable) to the bus when the user touches the button. The available range is -671088.625 to 670760.9375.

The “**state-dependent**” LED illumination mode is analogous as for the Scaling Constant and Counter Constant functions.

- **Dimmer:** implements a one-button light control that sends orders to the KNX bus, which can then be executed by light dimmers. These orders consist in:

- Switch-on / Switch-off orders (on short presses).
- Step dimming orders (on long presses) and the subsequent stop order once the button is released.

Being a one-button control, the **switch orders will alternate** (on / off) for every short press, and so will do the step dimming orders (increase / decrease) for every long press. However, there are some exceptions to this alternation:

- On a long press: an increase dimming order will be sent if the light is found to be off (according to the status object). On the other hand, a decrease order will be sent if it is found to be 100%.
- On a short press: a switch-on order will be sent if the light is found to be off (according to the status object). On the other hand, a switch-off order will be sent if it is found to be on (value greater than 0%).

Note that the device considers that the **current light level** is the value of a specific one-byte object provided to be written from the KNX bus (i.e., to receive feedback from the dimmer). This object is internally updated after a short or long press, but linking it to the real dimmer status is highly advisable.

Under a “**state-dependent**” LED illumination, the LED will remain on/off according to the value of the aforementioned status object (i.e., off when the value is 0% and on in any other case).

Note: *after a bus recovery, the light dimmer should send back the status object so the control and the LED update their own state, instead of simply recovering the previous one*

- **Shutter:** implements a one-button shutter control that sends orders to the KNX bus, which can then be executed by an actuator.

Two control types can be configured:

- Standard: the device will react to both long and short presses, being possible to send the bus the following commands:
 - Move (raise / lower) orders (on **long presses**).

- Stop / Step orders (on **short presses**).

Being a one-button control, the direction of the motion will alternate (upwards / downwards) for both the move and the step orders after every long press. However, there are some exceptions to this alternation:

- On a short press: a step-up order will be sent if the last long press made the shutter move up, or if the current position is found to be 100%. On the other hand, a step-down order will be sent if the last long press made the shutter move down or if the current position is found to be 0%.
- On a long press: a move-up order will be sent if the last short press caused a step-down order or if the current position is found to be 100%. On the other hand, a move-down order will be sent if the last short press caused a step-up order or if the current position is found to be 0%.

As usual in the KNX standard, **stop/step orders** are interpreted by the actuators as a request to move the slats one step up or down (in case the shutter is still) or as a request to interrupt the motion of the shutter (in case it is already moving up or down).

TMD-Display is aware of the current **position of the shutter** through a specific object which should be linked to the analogous object of the shutter actuator in order to receive feedback.

- Hold & Release: the device will send an order to move the shutter as soon as the button is touched, and the order to stop it as soon as it is released. Hence, short or long touches have the same effect: the shutter will remain in motion as long as the user keeps holding the button.

The direction of this motion (upwards or downwards) will **alternate** with every touch, according to the following sequence: downwards → upwards → downwards → ...

However, there are some exceptions to this alternation:

- If the position of the shutter is found to be 0%, the next order will lower the shutter.

- If the position of the shutter is found to be 100%, the next order will raise the shutter.

TMD-Display is aware of the current **position of the shutter** through a specific object which should be linked to the analogous object of the shutter actuator, in order to receive feedback. This object is initialised with value “50%” after a download or a bus failure; therefore, the actuator is required to update it with the real value after the bus recovery.

The “**state-dependent**” LED illumination mode is not available for this function.

- **Enumeration:** implements a one-button enumeration control that sends one-byte (unsigned) values to the KNX bus. This control is completely analogous to the Enumeration control in pair buttons (see section 2.3.3), however the object is sent to the bus when the button is pressed (not 1.5 seconds later). Moreover, in this case there is no option to link it to the display.

The “**state-dependent**” LED mode is not available for this function.

- **[Climate] Fan:** implements a fan control which sends to the KNX bus values in order to change the fan speed level. This function is similar to the pair button fan control described in section 2.3.3, (however in this case the object is sent to the bus immediately after the button is pressed).

ETS PARAMETERISATION

When an individual button has been enabled, a specific tab (“**Button Xn**”) becomes available under “Buttons” in the tree on the left.




Figure 42 Individual Button.


Note: the INFO textboxes are functionless (they simply bring the option to add a description to each button of the project) and can be hidden if desired. See section 2.2.6.

The main parameter that needs to be configured is:

- **Function:** sets the desired function for the button: “Disabled”, “Binary”, “Hold & Release”, “Two Objects (short press / long press)” or “Scene”, “Scaling constant”, “Counter constant”, “Float constant”, “Dimmer”, “Shutter” and “Enumeration”.

Depending on the function, some more parameters are involved (as described next). Please note that in the next pages “[Xn]” is used as a general notation for the communication objects, where “X” depends on the button pair (A, B, etc.) and “n” depends on the particular button within the pair (1 or 2).

Disabled



Function	Disabled
LED illumination control	Dedicated object
Object value	0 = Off; 1 = On

Figure 43 Individual Button – Disabled.

- **LED illumination control:** sets the behaviour of the LED on the button. The options are “Disabled” and “Dedicated object” (see ANNEX I: LED Illumination Modes for details about each option).

In case of selecting the latter, object “[Xn] LED On/Off” will be included in the project topology (the desired values to make the LED turn on/off must be set through “**Object Value**”).

Note: this parameter will remain hidden unless having selected “Configure every button (pair) separately” in “**LED Illumination Control (All Buttons)**” (see 2.3.1).

Switch

Function	Switch
Action	Toggle 0/1
LED illumination control	State-dependent

Figure 44 Individual Button - Switch.

- **Action:** sets the value to be sent to the bus (through object “[Btn] [Xn] Switch”) when the user touches the button. The options are “Send 0”, “Send 1” and “Toggle 0/1”.
- **LED illumination control:** analogous to the homonymous parameter for the “Disabled” function (see above). The options in this case are “Regular”, “State dependent” and “Dedicated object”.

Hold & Release

Function	Hold & Release
Action on Hold	Send 1
Action on Release	Send 0
LED illumination control	Regular

Figure 45 Individual Button – Hold & Release.

- **Action on Hold:** sets the value to be sent to the bus (through “[Btn] [Xn] Hold & Release”) when the user touches the button. The options are “Send 0” and “Send 1” (default).
- **Action on Release:** sets the value to be sent to the bus (again, through “[Btn] [Xn] Hold & Release”) when the user stops touching the button. The options are “Send 0” (default) and “Send 1”.
- **LED illumination control:** analogous to the homonymous parameter for the “LED Indicator” and “Switch” functions (see above). The options in this case are “Regular” and “Dedicated object”.

Two Objects (Short Press / Long Press)

Function	Two Objects (short press / long press)
Long press threshold time	5 ds
Action on Short press	Send 0
Action on Long press	Send 0
LED illumination control	State dependent
State Object	Short Press Object

Figure 46 Individual Button – Two Objects (short press / long press).

- **Long Press Threshold Time:** sets the minimum time the user should hold the button in order to consider it a long press. The available range is 5 to 50 tenths of a second, being 5 tenths the default value.
- **Action on Short press:** sets the value to be sent to the bus (through “[Btn] [Xn] Two switches - Short press”) when the user short-presses the button. The options are “Send 0”, “Send 1”, “Toggle 0/1” and “Send 1-byte value”. In case of selecting the latter, an additional parameter (“**Value**”) will be displayed to enter the desired one-byte value (0 - 255).
- **Action on Long press:** sets the value to be sent to the bus (through “[Btn] [Xn] Two switches - Long press”) when the user long-presses the button. The options are the same as for the short press.
- **LED illumination control:** analogous to the homonymous parameter for the “LED Indicator”, “Switch” and “Hold & Release” functions (see previous pages). The options in this case are “Regular”, “State dependent” and “Dedicated object”.

Selecting “State dependent” brings an additional parameter, “**LED Illumination State Object**”, to make the state of the LED correspond either to object “[Btn] [Xn] Two objects - Short press” (“Short Press Object”) or to object “[Btn] [Xn] Two objects - Long press” (“Long Press Object”).

Scene

Function	Scene
Action	Run scene
Scene number	1
LED illumination control	Dedicated object
Object value	0 = Off; 1 = On

Figure 47 Individual Button – Scene.

- **Action:** sets whether the value to be sent to the KNX bus (through “[**General**] **Scene: send**”) when the user touches the button will always be a scene run request (“Run scene”) or –depending on the length of button press– a scene run or save request (“Run (short press) + Save (3s press) scene”).
- **Scene number:** number of the scene (1 – 64) to be sent to the bus, both in the case of the run requests and the save requests.
- **LED illumination control:** analogous to the homonymous parameter for all the above functions (see previous pages). The options in this case are “Regular”, and “Dedicated object”.

Scaling Constant / Counter Constant / Float Constant

Function	Scaling constant
Value	0 %
LED illumination control	State dependent

Figure 48 Individual Button - Scaling Constant.

- **Value:** sets the value to be sent to the KNX bus when the user touches the button. The available range and the object through which the value is sent depends for each as the table below shows.

In case of selecting Counter Constant, two specific parameters (“**Size**” and “**Signed**”) will be displayed to respectively define the size of the constant (“1 byte” or “2 bytes”) and whether it is a signed value or an unsigned value. Depending on that, the range and the name of the object will vary.

	Available Values	Name of the Object
Scaling Constant	0% – 100%	[Btn] [Xn] Scaling
Counter Constant	0 – 255 -128 – 127 0 – 65535 -32768 – 32767	[Btn] [Xn] Counter – 1 byte unsigned [Btn] [Xn] Counter – 1 byte signed [Btn] [Xn] Counter – 2 byte unsigned [Btn] [Xn] Counter – 2 byte signed
Float Constant	-671088.64 – 670760.96	[Btn] [Xn] Float

Table 3 Scaling Constant Values

- **LED illumination control:** analogous to the homonymous parameter for all the above functions (see previous pages). The options in this case are “Regular”, “State dependent” and “Dedicated object”.

Dimmer

Function	Dimmer
Step	50%
LED illumination control	Dedicated object
Object value	0 = Off; 1 = On

Figure 49 Individual Button - Dimmer.

The (alternating) switch orders will be sent through the “[Btn] [Xn] Light - On/Off” one-bit object, while the (alternating) increase/decrease/stop orders will be through the “[Btn] [Xn] Light - Dimming” four-bit object.

On the other hand, the “[Btn] [In] Light Dimming (Status)” one-byte object may be linked to the light level status object of the dimmer (in fact, this object is only intended to receive values from the bus, not to send them). As explained in 2.3.4, the state-dependent LED lighting will be determined by the value of this object (LED off at 0% and on at any other level).

The parameters for this function are:

- **Step:** defines the dimming step (“100%”, “50%”, “25%”, “12.5%”, “6.25%”, “3.1%” or “1.5%”) to be sent (through “[Btn] [Xn] Light - Dimming”) to the light dimmer with every long press.

Note: since dimmers typically do not apply the new light level immediately (i.e., the step is performed progressively) and since TMD-Display sends an order to interrupt the step dimming once the user releases the button, it is advisable to configure a step of 100%. This way, the user can perform any dimming step by simply leaving the button pressed and then releasing it, without needing to make successive button presses.

- **LED illumination control:** analogous to the homonymous parameter for all the above functions (see previous pages). The options in this case are “Regular”, “State dependent” and “Dedicated object”.

Shutter

Function	Shutter
Type	Standard
LED illumination control	Dedicated object
Object value	0 = Off; 1 = On

Figure 50 Individual Button - Shutter.

The (alternating) move up/down orders will be sent through the “[Btn] [Xn] Shutter - Move” one-bit object, while the (alternating) step up/down orders will be through the “[Btn] [Xn] Shutter - Stop / Step” one-bit object.

Additionally, a one-byte object (“[Btn] [Xn] Shutter Position”) is provided to link it to the position status object of the shutter actuator (in fact, this object is only intended to receive values from the bus, not to send them). As explained in 0, the alternation of the move up/down and the step up/down requests will be conditioned to these statuses, to prevent sending ineffective requests.

The parameters for this function are:

- **Type:** sets the desired control type: “Standard” or “Hold & Release”, which have been described in section 2.3.4.
- **LED illumination control:** analogous to the homonymous parameter for all the previous functions (see previous pages). The options in this case are “Regular” and “Dedicated object”.

Enumeration

Function	Enumeration
# Enums	1
Value 1	0
LED illumination control	Dedicated object
Object value	0 = Off; 1 = On

Figure 51 Individual Buttons – Enumeration.

This control is completely analogous to the Enumeration control in pair-button controls (see section 2.3.3), but without the parameter to link the control to the display (in this case, the value is sent to the bus when the button is pressed).

- **# Enums:** number of states (up to 6) that will be distinguished. For every distinguished state, one parameter **Value j** will become available, in order to set the value sent through the communication object.
- **Value j:** numerical value (0 – 255) that will be sent through the object “[Btn] [Xn] Enumeration” when the user, after pressing the buttons, sets the control box to state j.
- **LED illumination control:** analogous to the homonymous parameter for all the previous functions (see previous pages). The options in this case are “Regular” and “Dedicated object”.

[Climate] Fan

Function	[Climate] Fan
Control Type	1 bit (decrease/increase)
Speed Levels	3
Sending type	Always send 1
Auto Mode	<input type="checkbox"/>
Allow Speed 0	<input type="checkbox"/>
LED illumination control	State-dependent

Figure 52 Individual Buttons – [Climate] Fan.

This control is analogous to the Fan control in pair buttons (see section 2.3.3).

The objects that depending on the configuration will send the orders to the bus are in this case the following:

- “[Btn] [Xn] Fan Control (1 bit)”
- “[Btn] [Xn] Fan Control Scaling”
- “[Bnt] [Xn] Fan Control Enumerated”

The status object (“[Btn] [Xn] Fan - State”) will be percentage-type or enumerated-type depending on the configuration.

In case of opting for a **one-bit** fan control, one special parameter will show up instead of the “**Cyclical**” parameter (which in the single-button control only applies to the **scaling** and **enumerated** fan controls):

- **Sending Type:** “Always Send 1” (after every button press, one “1” will be sent to the bus, i.e., the direction of the speed regulation will always be upwards) or “Send 0 or 1 According to the State Object” (the direction of the fan control will be upwards or downwards depending on the current state, as explained below).

The first option makes sense when the fan actuator implements a **cyclical control** (after the maximum fan level, a further increase order switches to the minimum level).

Being single-button, the **direction (upwards/downwards) of the control** will always be determined by the current value of the status object (except in the aforementioned “Always Send 1” one-bit case):

- **Upwards** if already at the minimum level.
- **Downwards** if already at the maximum level.
- In any other case, the direction will be the same as in the previous press.

Note that depending on how many speed levels have been configured and on whether the Auto mode has been left disabled or has been enabled with a dedicated object or not, the minimum and maximum levels of the range may not always be the same. See section 2.3.3 for further details.

2.4 DISPLAY

2.4.1 CONFIGURATION

TMD-Display features a **1.8" 128x64 pixel back-lit monochrome screen** with black background and white icons and fonts.

This screen can show useful information to the user, related to the current state of other devices or of its own controls.

The information provided by the display can consist in icons (with a resolution up to 28 x 22 pixels) or alphanumeric characters (texts). Please refer to the specific document "**Icons in TMD-Display One**" (available at the Zennio homepage, www.zennio.com) to see the list of available icons.



Figure 53 Some icons from TMD-Display One.

Three **different font sizes** for the alphanumeric characters are available: **Small**, **Big** and **Extra** (this one only for numeric characters).

As TMD-Display One offers the user a sole control page (instead of alternating, browsable pages), all the content of the display is shown permanently. It only gets hidden when the screensaver or some other special messages (welcome, locking or cleaning) are superimposed.

The screen is divided into 4 zones (**single** boxes –or *big* boxes–), named “a”, “b”, “c” and “d”, each of which can be further divided into two **double** boxes –or small boxes–. Each box consists of two areas:

- Lower area, where the box name (configurable through the parameter **Label**) is represented, with the Small text size. The text length depends on the box size: maximum 12 characters for big boxes and 6 characters for small boxes (if the text does not fit in the box, it will be truncated). If this label is left empty, then the indicator fills the box.

- Upper area, where the **Indicator** is represented. There are up to four representation modes, configurable in parameters for each indicator: **Permanent** (always shown), **Temporary** (shown for a moment when the value changes or after a bus recovery), **Intermittent** (intermittent indicator), and **Progressive** (the icon is progressively drawn from top to bottom).

The boxes in the screen can be assigned different functions, as described next.

ETS PARAMETERISATION

An independent tab for the parameterisation of the Display is shown in ETS by default. While all the zones remain disabled, it will only contain a sub-tab named Configuration.





Figure 54 Display – Configuration.

One drop-down list is shown per zone. The options under it are:

- Disabled. See section 2.4.2.
- Single (one big box). Selecting this option brings a new tab to the tree on the left (named “**Box X**”, where X depends on the display zone). See section 2.4.3.
- Double (two small boxes). Selecting this brings the checkboxes “**Box X1**” and “**Box X2**” (where X depends on the display zone), which turn each of the two zones enabled or disabled. Depending on this, up to two new tabs (named “**Box Xn**”) will be included in the tree on the left. See section 2.4.4.

There is also a checkbox named **Advanced options**, which permit configuring the border lines and the representation of the indicators.



Advanced options <input checked="" type="checkbox"/>	
Border lines	Invisible line in every border
Indicator representation	All indicators are type "permanent"
Object to show/hide the indicator	Not needed

Figure 55 Display - Configuration - Advanced options.

● **Border lines:** lets selecting how the box border lines will be represented:

- Solid line in every border,
- Invisible line in every border,
- Broken line in every border,
- Customize every border.

In case of selecting "Customize every border", an independent tab appears under Display to configure each box border line (see section 2.4.5).

● **Indicator representation:** defines the representation of the indicators on the display. The available options are:

- All indicators are type "permanent",
- Every indicator is configured separately.

In case of selecting "Every indicator is configured separately", there will be a specific parameter for every box to select the desired indicator representation.

● **Object to show/hide the indicator:** shows or hides a parameter in the configuration screen of each box to let the integrator add the project a one-bit object per box to show or hide its indicator in runtime.

- Not needed,
- Enable the option in every box.

2.4.2 DISABLED

While a display zone remains disabled, it does not represent anything and cannot be linked to any button – it will remain empty.

ETS PARAMETERISATION

This function has no related parameters.

2.4.3 SINGLE

Single boxes have a size of 64 x 32 pixels. The display can be divided into up to four single boxes.

Single boxes can be assigned the following types of indicators:

- **Icon:** the indicator will represent an icon according to the value of an object. Depending on the type of object there are two types of icons:
 - One bit: an icon represents the On state and another one represents the Off state.
 - Enumeration: up to six different states can be represented through one icon each.
- **Number:** the indicator will represent a number (received through the associated object) and a three-character text representing the units. Different number types are available for the different object types: Scaling, Counter (1 byte unsigned), Counter (1 byte signed), Counter (2 bytes unsigned), Counter (2 bytes signed), Counter (4 bytes unsigned), Float (2 bytes).
- **Text:** the indicator will represent a text according to the value of an object. This indicator is totally analogous to the Icon indicator, but each value is associated to a text instead of an icon. The types are the same:
 - One bit: a text represents the On state and another one represents the Off state.
 - Enumeration: up to six different states can be represented through one text each.

- **Time of day:** represents the current time (“hh:mm” in 24-hour format). Note that the time of day must be set through the bus by an external reference. In addition, in the absence of power the clock will get outdated.
- **Text from object:** represents a string (up to 14 characters) received through the corresponding communication object.
- **[Climate] Temperature:** represents temperature values as received through the related communication object. Values in the range [-99, 199] °C are available. Values out of range will be replaced by the corresponding limit.

When the value contains decimals, only the first one will be shown, and it will be represented in a smaller size. Also, if the decimal part does not fit, the number will be rounded to the nearest integer.

- **[Climate] Mode:** represents climate modes as received through the associated communication object. There are two Mode Types:
 - Heat/Cool: only the Heat and Cool modes will be represented, according to the value of a one-bit object.
 - Extended: up to five HVAC climate modes will be represented, according to the value received through a specific one-byte object. The icons are represented with a progressive shift in the box, i.e., the first mode is shown at the left and the last at the right, with the exception of the Auto mode, which is represented in the centre of the box.

If the object value does not correspond to a valid mode, no icon will be displayed.

- **[Climate] Fan:** represents fan speeds, according to the value of the corresponding object. There are up to 4 fan speed levels: Off/Auto, Min, Med, Max. The number of levels can be customised, as explained later.

As with climate modes, the icons of the successive levels are represented with a progressive shift, but without hiding the preceding ones.

- **[Climate] On/Off + Mode + Status:** climate status indicator with three one-bit objects associated: On/Off, Mode and Status. The icon represented depends on the value of these three objects, as explained in next section.

ETS PARAMETERISATION

When a display zone has been configured as Single, a specific tab (“**Box x**”) becomes available under “Display” in the tree on the left.




Figure 56 Display – Box a.

The main parameters that need to be configured are:

- **Label:** sets the box name (see section 2.4).
- **Indicator:** sets the desired indicator to display in the box: “Icon”, “Number”, “Text”, “Time of day”, “Text from object”, “[Climate] Temperature”, “[Climate] Mode”, “[Climate] Fan” or “[Climate] On/Off + Mode + Status”.

Depending on the indicator, some more parameters are shown, as described next. Please note that in the next pages the general notation “[x]” is used for the name of the communication objects, as “x” depends on the display zone (a, b, etc.).

Icon

Indicator	Icon
Type	1 bit
Select icon for 0	No icon
Representation	Permanent
Select icon for 1	No icon
Representation	Permanent
Object to show/hide indicator	<input checked="" type="checkbox"/>

Figure 57 Display indicator – Icon – 1 bit.

● Type:

- “1 bit”: the icon represented depends on the value of the one-bit object “[Disp] [x] Icon – 1 bit”. When selecting this type, the following parameters need to be configured:

- **Select icon for 0/1**: sets the icon to display for each value.
- **Representation**: sets the icon representation. The options are: “Permanent”, “Temporary”, “Intermittent” and “Progressive”.

Note: *this parameter will remain hidden unless having selected “Every indicator is configured separately” in “**Indicator representation**” (see section 2.4).*

- “Enumeration”: the icon represented depends on the value of the one-byte object “[Disp] [x] Icon – Enumeration”. When selecting this type, the following parameters need to be configured.

The screenshot shows a configuration window for an indicator. The 'Indicator' dropdown is set to 'Icon'. The 'Type' dropdown is set to 'Enumeration'. The 'How many values ?' field is set to '1'. The 'Value' field is set to '0'. The 'Icon' dropdown is set to 'No icon'. The 'Representation' dropdown is set to 'Permanent'. The 'Object to show/hide indicator' checkbox is checked.

Figure 58 Display indicator – Icon – Enum.

- **How many values**: sets the number of states of the enumerated list. Up to 6 are possible. For each element the following three parameters need to be configured.
 - **Value**: sets the numerical value assigned to the state (0 to 255).
 - **Icon**: sets the icon to be displayed when the above value is received.
 - **Representation**: sets the icon representation. The options are:

“Permanent”, “Temporary”, “Intermittent” and “Progressive”.

Note: this parameter will remain hidden unless having selected “Every indicator is configured separately” in “**Indicator representation**” (see section 2.4)

- **Object to show/hide indicator:** enables or disables a one-bit object (“**[Disp] [x] Show/Hide indicator**”) to show or hide the indicator in runtime (1 = Show indicator; 0 = Hide indicator).

Note: this parameter will remain hidden unless having selected “Enable the option in every box” in “**Object to show/hide the indicator**” (see section 2.4).

Number

Indicator	Number
Type	Scaling
Font size	Big
Representation	Permanent
Object to show/hide indicator	<input checked="" type="checkbox"/>

Figure 59 Display indicator – Number – Scaling.

- **Type:** sets the type of the number indicator. The options are: “Scaling”, “Counter (1 byte unsigned)”, “Counter (1 byte signed)”, “Counter (2 bytes unsigned)”, “Counter (2 bytes signed)”, “Counter (4 bytes unsigned)”, “Float (2 bytes)”.
- **Font size:** sets the font size of the number. The options are: “Small”, “Big” and “Extra”.
- **Suffix (units):** sets a label that will be shown next to the indicator. Up to three characters are possible.

Note: this parameter is not available for *Scaling*, as the suffix is always “%”.

- **Suffix font size:** sets the font size of the above suffix. The options are: “Small” and “Big”.

Note: this parameter is not available for Scaling, as the suffix font size is always “Small”.

- **Representation:** sets the indicator representation. The options are: “Permanent”, “Temporary”, “Intermittent” and “Progressive”.

Note: this parameter will remain hidden unless having selected “Every indicator is configured separately” in “**Indicator representation**” (see section 2.4).

- **Object to show/hide indicator:** enables or disables a one-bit object (“**[Disp] [x] Show/Hide indicator**”) to show or hide the indicator (1 = Show indicator; 0 = Hide indicator).

Note: this parameter will remain hidden unless having selected “Enable the option in every box” in “**Object to show/hide the indicator**” (see section 2.4).

Text

Indicator	Text
Type	1 bit
Font size	Small
Value 0:	
Text	
Representation	Permanent
Value 1:	
Text	
Representation	Permanent
Object to show/hide indicator	<input checked="" type="checkbox"/>

Figure 60 Display indicator – Text – 1 bit.

- **Type:**
 - “1 bit”: the text represented depends on the value of the one-bit object “**[Disp] [x] Text – 1 bit**”. When selecting this type, the following parameters need to be configured.

- **Value 0/1: Text:** sets the text to be displayed for each value. Maximum 12 characters allowed.
- **Representation:** sets the text representation. The options are: “Permanent”, “Temporary”, “Intermittent” and “Progressive”.

Note: *this parameter will remain hidden unless having selected “Every indicator is configured separately” in “**Indicator representation**” (see 2.4).*

- “Enumeration”: the icon represented depends on the value of the one-byte object “[Disp] [x] Text – Enumeration”. When selecting this type, the following parameters need to be configured.

Figure 61 Display indicator – Text – Enumeration.

- **How many elements:** sets the number of states of the enumerated list. Up to 6 states are possible. For each state, the following three parameters need to be configured.
 - **Value:** sets the numerical value assigned to the state (0 to 255).
 - **Icon:** sets the text to be displayed when the above value is received.
 - **Representation:** sets the text representation. The options are: “Permanent”, “Temporary”, “Intermittent” and “Progressive”.


Note: *this parameter will remain hidden unless having selected “Every indicator is configured separately” in “**Indicator**”*

representation” (see section 2.4)

- **Font size:** sets the font size of the texts. The options are: “Small” and “Big”.
- **Object to show/hide indicator:** enables or disables a one-bit object (“**[Disp]** **[x]** **Show/Hide indicator**”) to show or hide the indicator (1 = Show indicator; 0 = Hide indicator).

Note: *this parameter will remain hidden unless having selected “Enable the option in every box” in “**Object to show/hide the indicator**” (see section 2.4).*

Time of day



Indicator	Time of day
Font size	Small
Representation	Permanent
Object to show/hide indicator	<input checked="" type="checkbox"/>

Figure 62 Display indicator – Time of day.

Once the device starts, the time should be updated by an external clock through the “**[General]** **Time of day**” three-byte communication object.


- **Font size:** sets the font size of the time label. The options are: “Small”, “Big” and “Extra”.
- **Representation:** sets the representation type. The options are: “Permanent”, “Temporary”, “Intermittent” and “Progressive”.

Note: *this parameter will remain hidden unless having selected “Every indicator is configured separately” in “**Indicator representation**” (see section 2.4).*

- **Object to show/hide indicator:** enables or disables a 1 bit object (“**[Disp]** **[x]** **Show/Hide indicator**”) to show or hide the indicator (1 = Show indicator; 0 = Hide indicator).

Note: this parameter will remain hidden unless having selected “Enable the option in every box” in **“Object to show/hide the indicator”** (see section 2.4).

Text from object



Indicator	Text from object
Font size	Small
Representation	Permanent
Object to show/hide indicator	<input checked="" type="checkbox"/>

Figure 63 Display indicator – Text from object.

The text to be shown is to be received through the **“[Disp] [x] Text from object”** 14-byte communication object.


- **Font size:** sets the font size of the text. The options are: “Small” and “Big”.
- **Representation:** sets the text representation. The options are: “Permanent”, “Temporary”, “Intermittent” and “Progressive”.

Note: this parameter will remain hidden unless having selected “Every indicator is configured separately” in **“Indicator representation”** (see section 2.4).

- **Object to show/hide indicator:** enables or disables a 1 bit object (**“[Disp] [x] Show/Hide indicator”**) to show or hide the indicator (1 = Show indicator; 0 = Hide indicator).

Note: this parameter will remain hidden unless having selected “Enable the option in every box” in **“Object to show/hide the indicator”** (see section 2.4).

[Climate] Temperature



Indicator	[Climate] Temperature
Font size	Extra
Representation	Permanent
Object to show/hide indicator	<input checked="" type="checkbox"/>

Figure 64 Display indicator – [Climate] Temperature

The temperature needs to be updated through the “[Disp] [x] (Climate) Temperature” two-byte communication object.


- **Font size:** sets the font size of the temperature label. The options are: “Small”, “Big” and “Extra”.
- **Representation:** sets the temperature representation. The options are: “Permanent”, “Temporary”, “Intermittent” and “Progressive”.

Note: *this parameter will remain hidden unless having selected “Every indicator is configured separately” in “**Indicator representation**” (see section 2.4).*

- **Object to show/hide indicator:** enables or disables a one-bit object (“[Disp] [x] Show/Hide indicator”) to show or hide the indicator (1 = Show indicator; 0 = Hide indicator).

Note: *this parameter will remain hidden unless having selected “Enable the option in every box” in “**Object to show/hide the indicator**” (see section 2.4).*

[Climate] Mode



Indicator	[Climate] Mode
Mode Type	Heat/Cool
Representation	Permanent
Object to show/hide indicator	<input checked="" type="checkbox"/>

Figure 65 Display indicator – [Climate] Mode – Heat/Cool.

The climate mode needs to be updated through the “[Disp] [x] (Climate) Mode” one-bit object or the “[Disp] [x] (Climate) Mode - Extended” one-byte object, depending on the following parameterisation:

- **Mode Type:** sets whether only the Heat and Cool modes should be represented (“Heat/Cool”) or up to five HVAC modes (“Extended”).
 - “Heat/Cool”: the icon (Heat or Cool) will depend on the value of the “[Disp] [x] (Climate) Mode” one-bit object.

- **“Extended”**: the icon represented will depend on the value of the “[Disp] [x] (Climate) Mode - Extended” one-byte object. When selecting this type, five checkboxes appear to select which HVAC modes should be available (“Auto”, “Heat”, “Cool”, “Fan” and “Dry”, as shown in Figure 66).

Mode Type	Extended
Auto	<input checked="" type="checkbox"/>
Heat	<input checked="" type="checkbox"/>
Cool	<input checked="" type="checkbox"/>
Fan	<input checked="" type="checkbox"/>
Dry	<input checked="" type="checkbox"/>

Figure 66 Display indicator – [Climate] Mode – Mode Type: Extended.

- **Representation**: sets the representation type. The options are: “Permanent”, “Temporary”, “Intermittent” and “Progressive”.

Note: *this parameter will remain hidden unless having selected “Every indicator is configured separately” in “Indicator representation” (see section 2.4).*

- **Object to show/hide indicator**: enables or disables a one-bit object (“[Disp] [x] Show/Hide indicator”) to show or hide the indicator (1 = Show indicator; 0 = Hide indicator).

Note: *this parameter will remain hidden unless having selected “Enable the option in every box” in “Object to show/hide the indicator” (see section 2.4).*

[Climate] Fan

Indicator	[Climate] Fan
Off/Auto [0%]	<input type="checkbox"/>
Number of levels	3: Min (0% - 33%); Med (34% - 67%); Max (68% - ...)
Representation	Permanent
Object to show/hide indicator	<input checked="" type="checkbox"/>

Figure 67 Display indicator – [Climate] Fan.

The value should be updated through the “[Disp] [x] Fan” one-byte communication object.

- **Off/Auto [0%]:** defines whether the Off/Auto level is required to be represented or not. If enabled, the following parameter shows up:

- **How to show Off/Auto status:** sets how to represent the Auto/Off state. The options are: “Auto-style (fan symbol + word “Auto”)”, “Off-style I (fan symbol + word “Off”)” and “Off-style II (clear the box)”.

- **Number of levels:** sets the number of fan speed levels. The available options depend on whether the Off/Auto level is enabled or not:

- **If Off/Auto is enabled:**

- “1: Max (1% - 100%)”,
- “2: Min (1% - 50%); Max (51% - 100%)”,
- “3: Min (1% - 33%); Med (34% - 67%); Max (68% - 100%)”

The value 0% does not correspond to any level, but to the Off/Auto state.

- **If Off/Auto is disabled:**

- “2: Min (0% - 50%); Max (51% - 100%)”,
- “3: Min (0% - 33%); Med (34% - 67%); Max (68% - 100%)”.


- **Representation:** sets the indicator representation. The options are: “Permanent”, “Temporary”, “Intermittent” and “Progressive”.

Note: *this parameter will remain hidden unless having selected “Every indicator is configured separately” in “Indicator representation” (see section 2.4).*

- **Object to show/hide indicator:** enables or disables a one-bit object (“[Disp] [x] Show/Hide indicator”) to show or hide the indicator (1 = Show indicator; 0 = Hide indicator).

Note: this parameter will remain hidden unless having selected “Enable the option in every box” in **“Object to show/hide the indicator”** (see section 2.4).

[Climate] On/Off + Mode + Status



Indicator: [Climate] On/Off + Mode + Status

Object to show/hide indicator: ☒

Figure 68 Display indicator – [Climate] On/Off + Mode + Status.

The icon to be represented depends on the value of three one-bit objects: “[Disp] [x] (Climate) On/Off”, “[Disp] [x] (Climate) On/Off - Mode” and “[Disp] [x] (Climate) On/Off - Status”:

- “[Disp] [x] (Climate) On/Off” = 0: no icon is represented.
- “[Disp] [x] (Climate) On/Off” = 1 and “[Disp] [x] (Climate) On/Off - Status” = 0, it means that the climate system is on but stopped. The icon represented will depend on the mode selected through “[Disp] [x] (Climate) On/Off - Mode” (1 = Heat or 0 = Cool). The representation type will be Permanent.
- If “[Disp] [x] (Climate) On/Off” = 1 and “[Disp] [x] (Climate) On/Off - Status” = 1, it means that the climate is on and running. The icon represented will depend on the mode selected through “[Disp] [x] (Climate) On/Off - Mode” (1 = Heat –with waves–, or 0 = Cool –with waves–). The representation type is Progressive.

Note: for this indicator, the representation type cannot be configured. It is always permanent or progressive, depending on the value of the objects, as explained above.

- **Object to show/hide indicator:** enables or disables a 1 bit object (“[Disp] [x] Show/Hide indicator”) to show or hide the indicator (1 = Show indicator; 0 = Hide indicator).

Note: *this parameter will remain hidden unless having selected “Enable the option in every box” in “Object to show/hide the indicator” (see section 2.4).*

2.4.4 DOUBLE

Double boxes have a size of 32 x 32 pixels, so the display can be divided into up to 8 double boxes (two per zone).

Double boxes can be assigned exactly the same types of indicators as Single boxes (see section 2.4.3 for details).

The only differences between the two types of boxes are:

- The **maximum number of characters** allowed (up to 6 characters for double boxes; for single boxes the limit is 12 characters).
- The **font size** for some indicators. For example, the Extra size is not allowed for time and temperature indicators.

ETS PARAMETERISATION

When a display zone has been set to Double, a specific tab (“**Box Xn**”) becomes available under “Display” in the tree on the left.

The ETS parameterisation of each indicator is exactly the same as for Single boxes. See section 2.4.3 for details.

Indicator	Icon
Type	Icon
Select icon for 0	Number
Representation	Text
Select icon for 1	Time of day
Representation	Text from object
Object to show/hide indicator	[Climate] Temperature
	[Climate] Mode
	[Climate] Fan
	[Climate] On/Off + Mode + Status
	Permanent
	<input checked="" type="checkbox"/>

Figure 69 Display – Box a1.

2.4.5 BORDERS

Divisions between the boxes can be drawn in three different styles: with **solid lines**, **dashed** (dotted), or **invisible** (without division line). This configuration may be common to all lines or separate for each, as shown in Figure 70.




Figure 70 Borders – Different configuration for each border.

ETS PARAMETERISATION

After selecting “Customize every border” in the **Border lines** parameter (see section 2.4), a new tab will be incorporated into the tree on the left.




Figure 71 Display – Borders.

To simplify the configuration, this screen is divided into three parts (see Figure 71 Display – Borders.): **Upper lines (vertical)**: configures the upper vertical lines **a1-a2**, **a2-b1** and **b1-b2**.

- **Middle lines (horizontal)**: configures the middle horizontal lines **a1-c1**, **a2-c2**, **b1-d1** and **b2-d2**.
- **Lower lines (vertical)**: configures the lower vertical lines **c1-c2**, **c2-d1** and **d1-d2**.

The options available for all the lines are: “Solid line”, “Invisible” and “Dotted line”.

2.5 INPUTS

TMD-Display One incorporates **2 analogue/digital inputs**, each configurable as a:

- **Binary Input**, for the connection of a pushbutton or a switch/sensor.
- **Temperature Probe**, to connect a temperature sensor (model ZN1AC-NTC68 S/E/F from Zennio).
- **Motion Detector**, to connect a motion detector (models ZN1IO-DETEC-P and ZN1IO-DETEC-X from Zennio).

Important:

- *This device does not include **luminosity measurement capabilities** (only motion detection). Therefore, the two models mentioned offer equivalent functionality when connected to this device.*
- *The two models mentioned incorporate a voltage selection microswitch on the rear side, which should be set to position “**Type B**”.*
- *Older models of the Zennio motion detector (e.g., ZN1IO-DETEC and ZN1IO-DETEC-N) will not work properly with TMD-Display.*

For detailed information about the functionality and the configuration of the related parameters, please refer to the following specific manuals, all of them available at the Zennio homepage (www.zennio.com):

- **Binary Inputs in TMD-Display One.**
- **Temperature Probe in TMD-Display One.**
- **Motion Detector in TMD-Display One.**

2.6 THERMOSTAT

TMD-Display One implements **one Zennio thermostat** which can be enabled and fully customised.

Please refer to the specific manual “**Zennio Thermostat for TMD-Display One**” (available at the Zennio homepage, www.zennio.com) for detailed information about the functionality and the configuration of the related parameters.

ANNEX I: LED ILLUMINATION MODES

The central LED indicator of every button, by default (in most functions), will turn on for a brief instant whenever the button is touched. This behaviour is referred to as the “**Regular Illumination**”.

However, in most cases it is possible to assign different behaviours to the LEDs. Which options are available will depend on the function parameterised for the button, but will always include some of the following:

- **Regular Illumination:** the LED will light for an instant once the button is touched.
- **State-Dependent Illumination:** the LED will or will not light, depending on the value of the communication object that corresponds to the function implemented by the button. The exact correspondence between the different values of the object and the different states of the LED may be slightly different from one type of control to another, and is detailed for each function.
- **State-Dependent Illumination (both LEDs):** only applies to buttons configured as pair controls. The two LEDs of the control will light or not, depending on the value of the related object and on the particular control type parameterised for that pair of buttons. The only difference compared to the previous case is that, under “both LEDs”, the two LEDs will always turn off or on simultaneously, as if it were a unique indicator consisting of two LEDs.
- **Dedicated Object:** the LED will light or not depending on the value (“0” or “1”, configurable) of a binary, independent object. In the case of the pair controls, the value “0” will make one of the LEDs light (leaving the other one off), while the value “1” will make them switch their states.

Note:

Regarding the LEDs, it is interesting to distinguish the following cases:

- *Disabled button: the LED will remain off, and the button will have no function.*
- *Button configured as “Individual” with “Disabled” function: the button will still have no function. The LED may be turned on/off through a binary object.*

- Button configured as any other control type: the behaviour of the LED will be configurable according to the following table (being also possible to leave it turned off).

		Disabled	Regular	State-dep.	State-dep. (both LEDs)	Dedicated object
PAIR	Switch		✓	✓	✓	✓
	Two Objects		✓	✓	✓	✓
	Dimmer		✓	✓	✓	✓
	Shutter		✓			✓
	Scaling		✓			✓
	Counter		✓			✓
	Enumeration		✓			✓
	Float		✓			✓
	[Climate] Temperature		✓			✓
	[Climate] Mode		✓	✓	✓	✓
	[Climate] Fan		✓			✓
INDIVIDUAL	LED Indicator					✓
	Binary		✓	✓		✓
	Hold & Rel.		✓			✓
	Two Objects		✓	✓		✓
	Scene		✓			✓
	Constants		✓	✓		✓
	Dimmer		✓	✓		✓
	Shutter		✓			✓
	Enumeration		✓			✓
	[Climate] Fan		✓	✓	✓	✓
DISABLED		✓				

Table 4 Functions vs. LED Illumination Options.

Although the behaviour of the LEDs can be configured independently for each control (see section 2.3.1), it is also possible to define a **general behaviour for all of them**

thus not being then necessary to configure the same option multiple times. In case of opting for a general configuration, the options are:

- **Regular Illumination.**
- **State-Dependent (where available).** Functions where “state-dependent” is not available will use the regular illumination.
- **State-Dependent (where available) (both LEDs).** Functions where “state-dependent” is not available will use the regular illumination.
- **Dedicated Object.** One binary communication object per control will be included in the project topology so that the LED of every control turns on/off depending on its own object.

ETS PARAMETERISATION

For details on the parameterisation of the LED illumination modes please refer to the pages that cover the specific function being assigned to the button (section 2.3).

In case of desiring a **similar behaviour for all of the LEDs**, please find the parameter “**LED Illumination Control (All Buttons)**” in the options of the General configuration screen. This parameter is explained in section 2.3.1.

ANNEX II: COMMUNICATION OBJECTS

- **“Functional range”** shows the values that, with independence of any other values permitted by the bus according to the object size, may be of any use or have a particular meaning because of the specifications or restrictions from both the KNX standard or the application program itself.

Number	Size	I/O	Flags	Data type (DPT)	Functional Range	Name	Function
1	3 Bytes	I	C - - W -	DPT_TimeOfDay	00:00:00 - 23:59:59	[General] Time of day	Time of day external reference
2	1 Byte	I	C - - W -	DPT_SceneNumber		[General] Scene: receive	0-63 (Run scene 1-64)
3	1 Byte		C T - - -	DPT_SceneControl	0-63; 128-191	[General] Scene: send	0-63 / 128-191 (Run/Save scene 1-64)
4	1 Bit	I	C - - W -	DPT_Enable	0/1	[General] Touch Locking	1 = Locked; 0 = Normal
	1 Bit	I	C - - W -	DPT_Enable	0/1	[General] Touch Locking	1 = Normal; 0 = Locked
5	1 Bit	I	C - - W -	DPT_Trigger	0/1	[General] Cleaning Function	1 = Clean now; 0 = Nothing
6	1 Bit	I	C - - W -	DPT_Trigger	0/1	[General] Welcome Greeting	1 = Welcome; 0 = Nothing
7	2 Bytes	I	C - - W -	DPT_Value_Temp	-273.00° - 670760.00°	[General] Screensaver - External temperature	Temperature to be shown on the screensaver
8	1 Bit	I	C - - W -	DPT_Switch	0/1	[General] LEDs & Disp - Brightness mode	0 = Normal; 1 = Night
	1 Bit	I	C - - W -	DPT_Switch	0/1	[General] LEDs & Disp - Brightness mode	0 = Night; 1 = Normal
9, 10, 11, 12	14 Bytes	I	C - - W -	DPT_String_ASCII		[General] Welcome Greeting - Line n	Text to show on the display at Line n
13	1 Bit		C T - - -	DPT_Switch	0/1	[General] Welcome back object	Switch object sent on Wake up
14	1 Byte	I	C - - W -	DPT_SceneNumber		[General] Translations - Select language	0 = Main; 1 = Lang. 2; ... ; 4 = Lang. 5 (Scene format)
15, 16, 17, 18, 19	1 Bit	I	C - - W -	DPT_Trigger	0/1	[General] Translations - Language n	1 = Choose this language; 0 = Nothing
20	2 Bytes	I	C - - W -	DPT_LanguageCodeAlpha2_ASCII		[General] Translations - Select language	Language selection through ISO 639-1 two letters code
21	1 Byte	I	C - - W -	DPT_SceneNumber		[General] Display - Contrast	0 = Level 1; ... ; 9 = Level 10 (Scene format)
22	1 Bit	I	C - - W -	DPT_Enable	0/1	[General] Sounds - Disabling button sound	0 = Disable sound; 1 = Enable sound
	1 Bit	I	C - - W -	DPT_Enable	0/1	[General] Sounds - Disabling button sound	0 = Enable sound; 1 = Disable sound
23	1 Bit	I	C - - W -	DPT_Trigger	0/1	[General] Sounds - Doorbell	1 = Play a doorbell sound; 0 = Nothing
	1 Bit	I	C - - W -	DPT_Trigger	0/1	[General] Sounds - Doorbell	0 = Play a doorbell sound; 1 = Nothing
24	1 Bit	I	C - - W -	DPT_Alarm	0/1	[General] Sounds - Alarm	1 = Play alarm intermittent sounds; 0 = Stop alarm sounds
	1 Bit	I	C - - W -	DPT_Alarm	0/1	[General] Sounds - Alarm	0 = Play alarm intermittent sounds; 1 = Stop alarm sounds
25	1 Bit		C T - - -	DPT_Switch	0/1	[General] Central area	Parameterized value is sent

26, 27, 28, 29, 30	1 Bit	I	C - - W -	DPT_Switch	0/1	[General] Welcome back object - Additional condition	Additional condition object n
31, 37, 43, 49, 55, 61, 67, 73	1 Bit	I	CT - W -	DPT_Switch	0/1	[Btn] [X] Switch	Left = 0; Right = 1
	1 Bit	I	CT - W -	DPT_Switch	0/1	[Btn] [X] Switch	Left = 1; Right = 0
	1 Bit	I	CT - W -	DPT_Switch	0/1	[Btn] [X] Two objects - Short press	Left = 1; Right = 0
	1 Bit	I	CT - W -	DPT_Switch	0/1	[Btn] [X] Two objects - Short press	Left = 0; Right = 1
	1 Bit		CT - - -	DPT_Switch	0/1	[Btn] [X] Light - On/Off	(Short press) Left = Off; Right = On
	1 Bit		CT - - -	DPT_Switch	0/1	[Btn] [X] Light - On/Off	(Short press) Left = On; Right = Off
	1 Bit		CT - - -	DPT_Step	0/1	[Btn] [X] Shutter - Stop/Step	(Short press) Left = Stop/Step down; Right = Stop/Step up
	1 Bit		CT - - -	DPT_Step	0/1	[Btn] [X] Shutter - Stop/Step	(Short press) Left = Stop/Step up; Right = Stop/Step down
	1 Bit		CT - - -	DPT_Trigger	0/1	[Btn] [X] Shutter - Stop	(End pressing) Left = Stop-down; Right = Stop-up
	1 Bit		CT - - -	DPT_Trigger	0/1	[Btn] [X] Shutter - Stop	(End pressing) Left = Stop-up; Right = Stop-down
	1 Bit	I	CT - W -	DPT_Heat_Cool	0/1	[Btn] [X] (Climate) Mode	Left = Cool; Right = Heat
	1 Bit	I	CT - W -	DPT_Switch	0/1	[Btn] [Xn] Switch	Send selected value on short press
	1 Bit	I	CT - W -	DPT_Switch	0/1	[Btn] [Xn] Hold & Release	Send selected values on hold and release presses
	1 Bit	I	CT - W -	DPT_Switch	0/1	[Btn] [Xn] Two objects - Short press	Send selected value on short press
	1 Bit		CT - - -	DPT_Switch	0/1	[Btn] [Xn] Light - On/Off	(Short press) Switch between On and Off
	1 Bit		CT - - -	DPT_Step	0/1	[Btn] [Xn] Shutter - Stop/Step	(Short press) 0 = Stop shutter / Step up; 1 = Stop shutter / Step down
	1 Bit		CT - - -	DPT_Trigger	0/1	[Btn] [Xn] Shutter - Stop	(End pressing) Stop shutter
	1 Bit		CT - - -	DPT_Bool	0/1	[Btn] [Xn] Fan control (1 bit)	0 = Decrease; 1 = Increase
	1 Bit		CT - - -	DPT_Bool	0/1	[Btn] [X] Fan control (1 bit)	0 = Decrease; 1 = Increase
32, 38, 44, 50, 56, 62, 68, 74	4 Bit	I	CT - W -	DPT_Control_Dimming	0x0 (Stop) 0x1 (Dec. by 100%) 0x2 (Dec. by 50%) ... 0x8 (Stop) 0x9 (Inc. by 100%) 0xA (Inc. by 50%) ... 0xF (Inc. by 1%)	[Btn] [X] Light - Dimming	(Long press) Left = Darker; Right = Brighter
	4 Bit	I	CT - W -	DPT_Control_Dimming	0x0 (Stop) 0x1 (Dec. by 100%) 0x2 (Dec. by 50%) ... 0x8 (Stop)	[Btn] [X] Light - Dimming	(Long press) Left = Brighter; Right = Darker

					0x9 (Inc. by 100%) 0xA (Inc. by 50%) ... 0xF (Inc. by 1%)		
	4 Bit	I	CT - W -	DPT_Control_Dimming	0x0 (Stop) 0x1 (Dec. by 100%) 0x2 (Dec. by 50%) ... 0x8 (Stop) 0x9 (Inc. by 100%) 0xA (Inc. by 50%) ... 0xF (Inc. by 1%)	[Btn] [Xn] Light - Dimming	(Long press) Switch between dimming up and down
33, 39, 45, 51, 57, 63, 69, 75	1 Bit	I	CT - W -	DPT_Switch	0/1	[Btn] [X] Two objects - Long press	Left = 0; Right = 1
	1 Bit	I	CT - W -	DPT_Switch	0/1	[Btn] [X] Two objects - Long press	Left = 1; Right = 0
	1 Bit		CT - - -	DPT_UpDown	0/1	[Btn] [X] Shutter - Move	(Long press) Left = Down; Right = Up
	1 Bit		CT - - -	DPT_UpDown	0/1	[Btn] [X] Shutter - Move	(Long press) Left = Up; Right = Down
	1 Bit		CT - - -	DPT_UpDown	0/1	[Btn] [X] Shutter - Move	(Start pressing) Left = Down; Right = Up
	1 Bit		CT - - -	DPT_UpDown	0/1	[Btn] [X] Shutter - Move	(Start pressing) Left = Up; Right = Down
	1 Bit		CT - - -	DPT_UpDown	0/1	[Btn] [Xn] Shutter - Move	(Long press) 0 = Up; 1 = Down
	1 Bit		CT - - -	DPT_UpDown	0/1	[Btn] [Xn] Shutter - Move	(Start pressing) Switch between up and down
	1 Bit	I	CT - W -	DPT_Switch	0/1	[Btn] [Xn] Two objects - Long press	Send selected value on long press
	1 Bit		CT - - -	DPT_Switch	0/1	[Btn] [Xn] Fan Control - Auto mode	Switch auto mode on long press
	1 Bit		CT - - -	DPT_Switch	0/1	[Btn] [Xn] Fan Control - Auto mode	Switch auto mode on short press
	1 Bit		CT - - -	DPT_Switch	0/1	[Btn] [X] Fan Control - Auto mode	Switch auto mode on long press
	1 Bit		CT - - -	DPT_Switch	0/1	[Btn] [X] Fan Control - Auto mode	Switch auto mode on short press
	1 Bit	I	CT - W -	DPT_Switch	0/1	[Btn] [Xn] LED On/Off	0 = Off; 1 = On
34, 40, 46, 52, 58, 64, 70, 76	1 Bit	I	CT - W -	DPT_Switch	0/1	[Btn] [Xn] LED On/Off	0 = On; 1 = Off
	1 Bit	I	CT - W -	DPT_Switch	0/1	[Btn] [X] LED On/Off	0 = Off; 1 = On
	1 Bit	I	CT - W -	DPT_Switch	0/1	[Btn] [X] LED On/Off	0 = On; 1 = Off
	1 Bit	I	CT - W -	DPT_Switch	0/1	[Btn] [X] LED On/Off	0 = On; 1 = Off
35, 41, 47, 53, 59, 65, 71, 77	1 Byte	I	CT - W -	DPT_Scaling	0% - 100%	[Btn] [X] Scaling	Left = Decrease percentage; Right = Increase percent.
	1 Byte	I	CT - W -	DPT_Scaling	0% - 100%	[Btn] [X] Scaling	Left = Increase percentage; Right = Decrease percent.
	1 Byte	I	CT - W -	DPT_Value_1_Ucount	0 - 255	[Btn] [X] Counter - 1-byte unsigned	Left = Decrease; Right = Increase
	1 Byte	I	CT - W -	DPST-5-10 DPST-6-10		[Btn] [X] Counter - 1-byte unsigned	Left = Increase; Right = Decrease
	2 Bytes	I	CT - W -	DPT_Value_2_Ucount	0 - 65535	[Btn] [X] Counter - 2-bytes unsigned	Left = Decrease; Right = Increase

2 Bytes	I	CT - W	DPT_Value_2_Ucount	0 - 65535	[Btn] [X] Counter - 2-bytes unsigned	Left = Increase; Right = Decrease
1 Byte	I	CT - W	DPT_Value_1_Ucount	0 - 255	[Btn] [X] Enumeration	Rotating value change on short press
2 Bytes	I	CT - W	9.xxx	-671088.64 - 670760.96	[Btn] [X] Float	Left = Decrease; Right = Increase
2 Bytes	I	CT - W	9.xxx	-671088.64 - 670760.96	[Btn] [X] Float	Left = Increase; Right = Decrease
2 Bytes	I	CT - W	DPT_Value_Temp	-273.00° - 670760.00°	[Btn] [X] (Climate) Temperature setpoint	Left = Decrease; Right = Increase
2 Bytes	I	CT - W	DPT_Value_Temp	-273.00° - 670760.00°	[Btn] [X] (Climate) Temperature setpoint	Left = Increase; Right = Decrease
1 Byte	I	CT - W	DPT_HVACContrMode	0 = Auto 1 = Heat 3 = Cool 9 = Fan 14 = Dry	[Btn] [X] (Climate) Mode - Extended	Rotating change of selected modes on short press
1 Byte	I	CT - W	DPT_Scaling	0% - 100%	[Btn] [Xn] Scaling	Send selected percentage value on short press
1 Byte	I	CT - W	DPT_Value_1_Ucount	0 - 255	[Btn] [Xn] Counter - 1-byte unsigned	Send selected value on short press
1 Byte	I	CT - W	DPT_Value_1_Count	-128 - 127	[Btn] [Xn] Counter - 1-byte signed	Send selected value on short press
2 Bytes	I	CT - W	DPT_Value_2_Ucount	0 - 65535	[Btn] [Xn] Counter - 2-bytes unsigned	Send selected value on short press
2 Bytes	I	CT - W	DPT_Value_2_Count	-32768 - 32767	[Btn] [Xn] Counter - 2-bytes signed	Send selected value on short press
2 Bytes	I	CT - W	9.xxx	-671088.64 - 670760.96	[Btn] [Xn] Float	Send selected value on short press
1 Byte	I	CT - W	DPT_Value_1_Ucount	0 - 255	[Btn] [Xn] Two objects - Short press (1-byte)	Send selected 1-byte value on short press
1 Byte	I	CT - W	DPT_Value_1_Ucount	0 - 255	[Btn] [Xn] Enumeration	Rotating value change
1 Byte	I	CT - W	DPT_Scaling	0% - 100%	[Btn] [Xn] Shutter Position	0 â€" 100%
1 Byte	I	CT - W	DPT_Scaling	0% - 100%	[Btn] [Xn] Light Dimming (Status)	0 â€" 100%
1 Byte	I	CT - W	DPT_Value_1_Count	-128 - 127	[Btn] [X] Counter - 1-byte signed	Left = Decrease; Right = Increase
1 Byte	I	CT - W	DPT_Value_1_Count	-128 - 127	[Btn] [X] Counter - 1-byte signed	Left = Increase; Right = Decrease
2 Bytes	I	CT - W	DPT_Value_2_Count	-32768 - 32767	[Btn] [X] Counter - 2-bytes signed	Left = Decrease; Right = Increase
2 Bytes	I	CT - W	DPT_Value_2_Count	-32768 - 32767	[Btn] [X] Counter - 2-bytes signed	Left = Increase; Right = Decrease
1 Byte	I	CT - W	DPT_Scaling	0% - 100%	[Btn] [X] Light Dimming (Status)	0 â€" 100%

1 Byte	CT---	DPT_Scaling	0% - 100%	[Btn] [Xn] Fan control (scaling)	0%, 33%, 67%, 100%
1 Byte	CT---	DPT_Scaling	0% - 100%	[Btn] [Xn] Fan control (scaling)	Auto, 25%, 50%, 75%, 100%
1 Byte	CT---	DPT_Scaling	0% - 100%	[Btn] [Xn] Fan control (scaling)	20%, 40%, 60%, 80%, 100%
1 Byte	CT---	DPT_Scaling	0% - 100%	[Btn] [Xn] Fan control (scaling)	0%, 25%, 50%, 75%, 100%
1 Byte	CT---	DPT_Scaling	0% - 100%	[Btn] [Xn] Fan control (scaling)	Auto, 33%, 67%, 100%
1 Byte	CT---	DPT_Scaling	0% - 100%	[Btn] [Xn] Fan control (scaling)	25%, 50%, 75%, 100%
1 Byte	CT---	DPT_Scaling	0% - 100%	[Btn] [Xn] Fan control (scaling)	100%
1 Byte	CT---	DPT_Scaling	0% - 100%	[Btn] [Xn] Fan control (scaling)	Auto, 50%, 100%
1 Byte	CT---	DPT_Scaling	0% - 100%	[Btn] [Xn] Fan control (scaling)	Auto, 100%
1 Byte	CT---	DPT_Scaling	0% - 100%	[Btn] [Xn] Fan control (scaling)	0%, 100%
1 Byte	CT---	DPT_Scaling	0% - 100%	[Btn] [Xn] Fan control (scaling)	50%, 100%
1 Byte	CT---	DPT_Scaling	0% - 100%	[Btn] [Xn] Fan control (scaling)	33%, 67%, 100%
1 Byte	CT---	DPT_Scaling	0% - 100%	[Btn] [Xn] Fan control (scaling)	0%, 50%, 100%
1 Byte	CT---	DPT_Value_1_Ucount	0 - 255	[Btn] [Xn] Fan control (enumerated)	1, 2
1 Byte	CT---	DPT_Value_1_Ucount	0 - 255	[Btn] [Xn] Fan control (enumerated)	0, 1, 2, 3, 4, 5
1 Byte	CT---	DPT_Value_1_Ucount	0 - 255	[Btn] [Xn] Fan control (enumerated)	Auto, 1, 2, 3, 4, 5
1 Byte	CT---	DPT_Value_1_Ucount	0 - 255	[Btn] [Xn] Fan control (enumerated)	1, 2, 3
1 Byte	CT---	DPT_Value_1_Ucount	0 - 255	[Btn] [Xn] Fan control (enumerated)	1, 2, 3, 4, 5
1 Byte	CT---	DPT_Value_1_Ucount	0 - 255	[Btn] [Xn] Fan control (enumerated)	Auto, 1, 2, 3, 4
1 Byte	CT---	DPT_Value_1_Ucount	0 - 255	[Btn] [Xn] Fan control (enumerated)	0, 1, 2, 3
1 Byte	CT---	DPT_Value_1_Ucount	0 - 255	[Btn] [Xn] Fan control (enumerated)	1, 2, 3, 4
1 Byte	CT---	DPT_Value_1_Ucount	0 - 255	[Btn] [Xn] Fan control (enumerated)	0, 1, 2, 3, 4
1 Byte	CT---	DPT_Value_1_Ucount	0 - 255	[Btn] [Xn] Fan control (enumerated)	1
1 Byte	CT---	DPT_Value_1_Ucount	0 - 255	[Btn] [Xn] Fan control (enumerated)	0, 1
1 Byte	CT---	DPT_Scaling	0% - 100%	[Btn] [Xn] Fan control (scaling)	0%, 20%, 40%, 60%, 80%, 100%
1 Byte	CT---	DPT_Scaling	0% - 100%	[Btn] [Xn] Fan control (scaling)	Auto, 20%, 40%, 60%, 80%, 100%
1 Byte	CT---	DPT_Value_1_Ucount	0 - 255	[Btn] [Xn] Fan control (enumerated)	Auto, 1, 2
1 Byte	CT---	DPT_Value_1_Ucount	0 - 255	[Btn] [Xn] Fan control (enumerated)	Auto, 1, 2, 3
1 Byte	CT---	DPT_Value_1_Ucount	0 - 255	[Btn] [Xn] Fan control (enumerated)	Auto, 1
1 Byte	CT---	DPT_Value_1_Ucount	0 - 255	[Btn] [Xn] Fan control (enumerated)	0, 1, 2
1 Byte	CT---	DPT_Scaling	0% - 100%	[Btn] [X] Fan control (scaling)	Auto, 25%, 50%, 75%, 100%
1 Byte	CT---	DPT_Scaling	0% - 100%	[Btn] [X] Fan control (scaling)	20%, 40%, 60%, 80%, 100%
1 Byte	CT---	DPT_Scaling	0% - 100%	[Btn] [X] Fan control (scaling)	0%, 25%, 50%, 75%, 100%
1 Byte	CT---	DPT_Scaling	0% - 100%	[Btn] [X] Fan control (scaling)	0%, 33%, 67%, 100%
1 Byte	CT---	DPT_Scaling	0% - 100%	[Btn] [X] Fan control (scaling)	Auto, 50%, 100%
1 Byte	CT---	DPT_Scaling	0% - 100%	[Btn] [X] Fan control (scaling)	Auto, 100%
1 Byte	CT---	DPT_Scaling	0% - 100%	[Btn] [X] Fan control (scaling)	100%
1 Byte	CT---	DPT_Scaling	0% - 100%	[Btn] [X] Fan control (scaling)	Auto, 33%, 67%, 100%
1 Byte	CT---	DPT_Scaling	0% - 100%	[Btn] [X] Fan control (scaling)	25%, 50%, 75%, 100%
1 Byte	CT---	DPT_Scaling	0% - 100%	[Btn] [X] Fan control (scaling)	0%, 50%, 100%
1 Byte	CT---	DPT_Scaling	0% - 100%	[Btn] [X] Fan control (scaling)	0%, 20%, 40%, 60%, 80%, 100%
1 Byte	CT---	DPT_Scaling	0% - 100%	[Btn] [X] Fan control (scaling)	50%, 100%

	1 Byte		C T - - -	DPT_Scaling	0% - 100%	[Btn] [X] Fan control (scaling)	33%, 67%, 100%
	1 Byte		C T - - -	DPT_Scaling	0% - 100%	[Btn] [X] Fan control (scaling)	Auto, 20%, 40%, 60%, 80%, 100%
	1 Byte		C T - - -	DPT_Scaling	0% - 100%	[Btn] [X] Fan control (scaling)	0%, 100%
	1 Byte		C T - - -	DPT_Value_1_Ucount	0 - 255	[Btn] [X] Fan control (enumerated)	Auto, 1, 2, 3, 4
	1 Byte		C T - - -	DPT_Value_1_Ucount	0 - 255	[Btn] [X] Fan control (enumerated)	1, 2
	1 Byte		C T - - -	DPT_Value_1_Ucount	0 - 255	[Btn] [X] Fan control (enumerated)	0, 1, 2, 3, 4, 5
	1 Byte		C T - - -	DPT_Value_1_Ucount	0 - 255	[Btn] [X] Fan control (enumerated)	Auto, 1, 2, 3, 4, 5
	1 Byte		C T - - -	DPT_Value_1_Ucount	0 - 255	[Btn] [X] Fan control (enumerated)	1, 2, 3
	1 Byte		C T - - -	DPT_Value_1_Ucount	0 - 255	[Btn] [X] Fan control (enumerated)	1, 2, 3, 4, 5
	1 Byte		C T - - -	DPT_Value_1_Ucount	0 - 255	[Btn] [X] Fan control (enumerated)	Auto, 1, 2
	1 Byte		C T - - -	DPT_Value_1_Ucount	0 - 255	[Btn] [X] Fan control (enumerated)	0, 1
	1 Byte		C T - - -	DPT_Value_1_Ucount	0 - 255	[Btn] [X] Fan control (enumerated)	Auto, 1, 2, 3
	1 Byte		C T - - -	DPT_Value_1_Ucount	0 - 255	[Btn] [X] Fan control (enumerated)	0, 1, 2
	1 Byte		C T - - -	DPT_Value_1_Ucount	0 - 255	[Btn] [X] Fan control (enumerated)	Auto, 1
	1 Byte		C T - - -	DPT_Value_1_Ucount	0 - 255	[Btn] [X] Fan control (enumerated)	0, 1, 2, 3, 4
	1 Byte		C T - - -	DPT_Value_1_Ucount	0 - 255	[Btn] [X] Fan control (enumerated)	0, 1, 2, 3
	1 Byte		C T - - -	DPT_Value_1_Ucount	0 - 255	[Btn] [X] Fan control (enumerated)	1, 2, 3, 4
	1 Byte		C T - - -	DPT_Value_1_Ucount	0 - 255	[Btn] [X] Fan control (enumerated)	1
36, 42, 48, 54, 60, 66, 72, 78	1 Byte	I	C T - W -	DPT_Value_1_Ucount	0 - 255	[Btn] [Xn] Two objects - Long press (1-byte)	Send selected 1-byte value on long press
	1 Byte	I	C T - W -	DPT_Value_1_Ucount	0 - 255	[Btn] [Xn] Fan - State	Enumerated Value
	1 Byte	I	C T - W -	DPT_Scaling	0% - 100%	[Btn] [Xn] Fan - State	0 - 100%
	1 Byte	I	C T - W -	DPT_Value_1_Ucount	0 - 255	[Btn] [X] Fan - State	Enumerated Value
	1 Byte	I	C T - W -	DPT_Scaling	0% - 100%	[Btn] [X] Fan - State	0 - 100%
79, 87, 95, 103, 111, 119, 127, 135	1 Bit	I	C - - W -	DPT_Switch	0/1	[Disp] [y] Show/Hide indicator	0 = Hide indicator; 1 = Show indicator
	1 Bit	I	C - - W -	DPT_Switch	0/1	[Disp] [yn] Show/Hide indicator	0 = Hide indicator; 1 = Show indicator
80, 88, 96, 104, 112, 120, 128, 136	1 Bit	I	C - - W -	DPT_Switch	0/1	[Disp] [y] Icon - 1-bit	Selected icon shown on new value reception
	1 Bit	I	C - - W -	DPT_Switch	0/1	[Disp] [y] Text - 1-bit	Parameterized text shown on new value reception
	1 Bit	I	C - - W -	DPT_Heat_Cool	0/1	[Disp] [y] (Climate) Mode	Mode icon is shown (0 = Cool; 1 = Heat)
	1 Bit	I	C - - W -	DPT_Switch	0/1	[Disp] [y] (Climate) On/Off	0 = Off (hide indicator); 1 = On (show mode or status)
	1 Bit	I	C - - W -	DPT_Switch	0/1	[Disp] [yn] Icon - 1-bit	Selected icon shown on new value reception
	1 Bit	I	C - - W -	DPT_Switch	0/1	[Disp] [yn] Text - 1-bit	Parameterized text shown on new value reception
	1 Bit	I	C - - W -	DPT_Heat_Cool	0/1	[Disp] [yn] (Climate) Mode	Mode icon is shown (0 = Cool; 1 = Heat)
	1 Bit	I	C - - W -	DPT_Switch	0/1	[Disp] [yn] (Climate) On/Off	0 = Off (hide indicator); 1 = On (show mode or status)
81, 89, 97, 105,	1 Byte	I	C - - W -	DPT_Value_1_Ucount	0 - 255	[Disp] [y] Icon - Enumeration	Selected icon shown on new value reception
	1 Byte	I	C - - W -	DPT_Scaling	0% - 100%	[Disp] [y] Icon - Range (scaling)	Selected icon shown on new value reception
	1 Byte	I	C - - W -	DPT_Scaling	0% - 100%	[Disp] [y] Number - Scaling	Object numeric value is shown

113, 121, 129, 137	1 Byte	I	C - - W -	DPT_Value_1_Ucount	0 - 255	[Disp] [y] Number - Counter (1-byte unsigned)	Object numeric value is shown
	1 Byte	I	C - - W -	DPT_Value_1_Count	-128 - 127	[Disp] [y] Number - Counter (1-byte signed)	Object numeric value is shown
	1 Byte	I	C - - W -	DPT_Value_1_Ucount	0 - 255	[Disp] [y] Text - Enumeration	Parameterized text shown on new value reception
	1 Byte	I	C - - W -	DPT_Scaling	0% - 100%	[Disp] [y] Level - Scaling	Level representing object value is shown
	1 Byte	I	C - - W -	DPT_Value_1_Ucount	0 - 255	[Disp] [y] Level - Counter (1-byte unsigned)	Level representing object value is shown
	1 Byte	I	C - - W -	DPT_Value_1_Count	-128 - 127	[Disp] [y] Level - Counter (1-byte signed)	Level representing object value is shown
	1 Byte	I	C - - W -	DPT_HVACContrMode	0 = Auto 1 = Heat 3 = Cool 9 = Fan 14 = Dry	[Disp] [y] (Climate) Mode - Extended	Mode icon is shown
	1 Byte	I	C - - W -	DPT_Scaling	0% - 100%	[Disp] [y] Fan	2 levels: Min (0% - 50%); Max (51% - 100%)
	1 Byte	I	C - - W -	DPT_Scaling	0% - 100%	[Disp] [y] Fan	3 levels: Min (0% - 33%); Med (34% - 66%); Max (67% - 100%)
	1 Byte	I	C - - W -	DPT_Scaling	0% - 100%	[Disp] [y] Fan	Off/Auto + 1 level: Off/Auto = 0%; Max (1% - 100%)
	1 Byte	I	C - - W -	DPT_Scaling	0% - 100%	[Disp] [y] Fan	Off/Auto + 2 levels: Off/Auto = 0%; Min (1% - 50%); Max (51% - 100%)
	1 Byte	I	C - - W -	DPT_Scaling	0% - 100%	[Disp] [y] Fan	Off/Auto + 3 levels: Off/Auto = 0%; Min (1% - 33%); Med (34% - 66%); Max (67% - 100%)
	1 Byte	I	C - - W -	DPT_Value_1_Ucount	0 - 255	[Disp] [y] Icon - Range (counter)	Selected icon shown on new value reception
	1 Byte	I	C - - W -	DPT_Scaling	0% - 100%	[Disp] [y] Text - Range (scaling)	Selected text shown on new value reception
	1 Byte	I	C - - W -	DPT_Value_1_Ucount	0 - 255	[Disp] [y] Text - Range (counter)	Selected text shown on new value reception
	1 Byte	I	C - - W -	DPT_Value_1_Ucount	0 - 255	[Disp] [yn] Icon - Enumeration	Selected icon shown on new value reception
	1 Byte	I	C - - W -	DPT_Scaling	0% - 100%	[Disp] [yn] Icon - Range (scaling)	Selected icon shown on new value reception
	1 Byte	I	C - - W -	DPT_Scaling	0% - 100%	[Disp] [yn] Number - Scaling	Object numeric value is shown
	1 Byte	I	C - - W -	DPT_Value_1_Ucount	0 - 255	[Disp] [yn] Number - Counter (1-byte unsigned)	Object numeric value is shown
	1 Byte	I	C - - W -	DPT_Value_1_Count	-128 - 127	[Disp] [yn] Number - Counter (1-byte signed)	Object numeric value is shown
	1 Byte	I	C - - W -	DPT_Value_1_Ucount	0 - 255	[Disp] [yn] Text - Enumeration	Parameterized text shown on new value reception
	1 Byte	I	C - - W -	DPT_Scaling	0% - 100%	[Disp] [yn] Level - Scaling	Level representing object value is shown
	1 Byte	I	C - - W -	DPT_Value_1_Ucount	0 - 255	[Disp] [yn] Level - Counter (1-byte unsigned)	Level representing object value is shown
	1 Byte	I	C - - W -	DPT_Value_1_Count	-128 - 127	[Disp] [yn] Level - Counter (1-byte signed)	Level representing object value is shown
	1 Byte	I	C - - W -	DPT_HVACContrMode	0 = Auto 1 = Heat 3 = Cool 9 = Fan 14 = Dry	[Disp] [yn] (Climate) Mode - Extended	Mode icon is shown
	1 Byte	I	C - - W -	DPT_Scaling	0% - 100%	[Disp] [yn] Fan	2 levels: Min (0% - 50%); Max (51% - 100%)
	1 Byte	I	C - - W -	DPT_Scaling	0% - 100%	[Disp] [yn] Fan	3 levels: Min (0% - 33%); Med (34% - 66%); Max (67% - 100%)

	1 Byte	I	C - - W -	DPT_Scaling	0% - 100%	[Disp] [yn] Fan	100%) Off/Auto + 1 level: Off/Auto = 0%; Max (1% - 100%)
	1 Byte	I	C - - W -	DPT_Scaling	0% - 100%	[Disp] [yn] Fan	Off/Auto + 2 levels: Off/Auto = 0%; Min (1% - 50%); Max (51% - 100%)
	1 Byte	I	C - - W -	DPT_Scaling	0% - 100%	[Disp] [yn] Fan	Off/Auto + 3 levels: Off/Auto = 0%; Min (1% - 33%); Med (34% - 66%); Max (67% - 100%)
	1 Byte	I	C - - W -	DPT_Value_1_Ucount	0 - 255	[Disp] [yn] Icon - Range (counter)	Selected icon shown on new value reception
	1 Byte	I	C - - W -	DPT_Scaling	0% - 100%	[Disp] [yn] Text - Range (scaling)	Selected text shown on new value reception
	1 Byte	I	C - - W -	DPT_Value_1_Ucount	0 - 255	[Disp] [yn] Text - Range (counter)	Selected text shown on new value reception
82, 90, 98, 106, 114, 122, 130, 138	2 Bytes	I	C - - W -	DPT_Value_2_Ucount	0 - 65535	[Disp] [y] Number - Counter (2-bytes unsigned)	Object numeric value is shown
	2 Bytes	I	C - - W -	DPT_Value_2_Count	-32768 - 32767	[Disp] [y] Number - Counter (2-bytes signed)	Object numeric value is shown
	2 Bytes	I	C - - W -	9.xxx	-671088.64 - 670760.96	[Disp] [y] Number - Float (2-bytes)	Object numeric value is shown
	2 Bytes	I	C - - W -	DPT_Value_2_Ucount	0 - 65535	[Disp] [y] Level - Counter (2-bytes unsigned)	Level representing object value is shown
	2 Bytes	I	C - - W -	DPT_Value_2_Count	-32768 - 32767	[Disp] [y] Level - Counter (2-bytes signed)	Level representing object value is shown
	2 Bytes	I	C - - W -	9.xxx	-671088.64 - 670760.96	[Disp] [y] Level - Float (2-bytes)	Level representing object value is shown
	2 Bytes	I	C - - W -	DPT_Value_Temp	-273.00° - 670760.00°	[Disp] [y] (Climate) Temperature	Object value is shown (-99Å°C to 199Å°C)
	2 Bytes	I	C - - W -	9.xxx	-671088.64 - 670760.96	[Disp] [y] Icon - Range (float)	Selected icon shown on new range of values reception
	2 Bytes	I	C - - W -	9.xxx	-671088.64 - 670760.96	[Disp] [y] Text - Range (float)	Selected text shown on new range of values reception
	2 Bytes	I	C - - W -	DPT_Value_2_Ucount	0 - 65535	[Disp] [yn] Number - Counter (2-bytes unsigned)	Object numeric value is shown
	2 Bytes	I	C - - W -	DPT_Value_2_Count	-32768 - 32767	[Disp] [yn] Number - Counter (2-bytes signed)	Object numeric value is shown
	2 Bytes	I	C - - W -	9.xxx	-671088.64 - 670760.96	[Disp] [yn] Number - Float (2-bytes)	Object numeric value is shown
	2 Bytes	I	C - - W -	DPT_Value_2_Ucount	0 - 65535	[Disp] [yn] Level - Counter (2-bytes unsigned)	Level representing object value is shown
	2 Bytes	I	C - - W -	DPT_Value_2_Count	-32768 - 32767	[Disp] [yn] Level - Counter (2-bytes signed)	Level representing object value is shown
	2 Bytes	I	C - - W -	9.xxx	-671088.64 - 670760.96	[Disp] [yn] Level - Float (2-bytes)	Level representing object value is shown
	2 Bytes	I	C - - W -	DPT_Value_Temp	-273.00° - 670760.00°	[Disp] [yn] (Climate) Temperature	Object value is shown (-99Å°C to 199Å°C)
	2 Bytes	I	C - - W -	9.xxx	-671088.64 - 670760.96	[Disp] [yn] Icon - Range (float)	Selected icon shown on new range of values reception
	2 Bytes	I	C - - W -	9.xxx	-671088.64 - 670760.96	[Disp] [yn] Text - Range (float)	Selected text shown on new range of values reception

83, 91, 99, 107, 115, 123, 131, 139	4 Bytes	I	C - - W -	DPT_Value_4_Ucount		[Disp] [y] Number - Counter (4-bytes unsigned)	Object numeric value is shown
	4 Bytes	I	C - - W -	DPT_Value_4_Ucount		[Disp] [y] Level - Counter (4-bytes unsigned)	Level representing object value is shown
	4 Bytes	I	C - - W -	DPT_Value_4_Ucount		[Disp] [yn] Number - Counter (4-bytes unsigned)	Object numeric value is shown
	4 Bytes	I	C - - W -	DPT_Value_4_Ucount		[Disp] [yn] Level - Counter (4-bytes unsigned)	Level representing object value is shown
84, 92, 100, 108, 116, 124, 132, 140	14 Bytes	I	C - - W -	DPT_String_8859_1		[Disp] [y] Text from object	Received text is shown
	14 Bytes	I	C - - W -	DPT_String_8859_1		[Disp] [yn] Text from object	Received text is shown
85, 93, 101, 109, 117, 125, 133, 141	1 Bit	I	C - - W -	DPT_Heat_Cool	0/1	[Disp] [y] (Climate) On/Off - Mode	0 = Cool; 1 = Heat. (Mode icon is shown when On/Off = 1, and Status = 0)
	1 Bit	I	C - - W -	DPT_Heat_Cool	0/1	[Disp] [yn] (Climate) On/Off - Mode	0 = Cool; 1 = Heat. (Mode icon is shown when On/Off = 1, and Status = 0)
86, 94, 102, 110, 118, 126, 134, 142	1 Bit	I	C - - W -	DPT_Switch	0/1	[Disp] [y] (Climate) On/Off - Status	0 = Halted; 1 = Running. (Status icon is shown when On/Off = 1, and Status = 1)
	1 Bit	I	C - - W -	DPT_Switch	0/1	[Disp] [yn] (Climate) On/Off - Status	0 = Halted; 1 = Running. (Status icon is shown when On/Off = 1, and Status = 1)
143	1 Byte	I	C - - W -	DPT_SceneControl	0-63; 128-191	[Thermostat] Scene Input	Scene Value
144, 145	2 Bytes	I	C - - W -	DPT_Value_Temp	-273.00° - 670760.00°	[T1] Temperature Source n	External Sensor Measure
146	2 Bytes	O	C T R - -	DPT_Value_Temp	-273.00° - 670760.00°	[T1] Effective Temperature	Effective Control Temperature
147	1 Byte	I	C - - W -	DPT_HVACMode	1=Comfort 2=Standby 3=Economy 4=Building Protection	[T1] Special Mode	1-byte HVAC Mode
148	1 Bit	I	C - - W -	DPT_Trigger	0/1	[T1] Special Mode: comfort	0=Nothing; 1=Trigger
	1 Bit	I	C - - W -	DPT_Switch	0/1	[T1] Special Mode: comfort	0=Off; 1=On
149	1 Bit	I	C - - W -	DPT_Trigger	0/1	[T1] Special Mode: standby	0=Nothing; 1=Trigger
	1 Bit	I	C - - W -	DPT_Switch	0/1	[T1] Special Mode: standby	0=Off; 1=On
150	1 Bit	I	C - - W -	DPT_Trigger	0/1	[T1] Special Mode: economy	0=Nothing; 1=Trigger
	1 Bit	I	C - - W -	DPT_Switch	0/1	[T1] Special Mode: economy	0=Off; 1=On
151	1 Bit	I	C - - W -	DPT_Trigger	0/1	[T1] Special Mode: protection	0=Nothing; 1=Trigger
	1 Bit	I	C - - W -	DPT_Switch	0/1	[T1] Special Mode: protection	0=Off; 1=On
152	1 Bit	I	C - - W -	DPT_Window_Door	0/1	[T1] Window Status (input)	0=Closed; 1=Open

153	1 Bit	I	C - - W -	DPT_Trigger	0/1	[T1] Comfort Prolongation	0=Nothing; 1=Timed Comfort
154	1 Byte	O	C T R - -	DPT_HVACMode	1=Comfort 2=Standby 3=Economy 4=Building Protection	[T1] Special Mode Status	1-byte HVAC Mode
155	2 Bytes	I	C - - W -	DPT_Value_Temp	-273.00° - 670760.00°	[T1] Setpoint	Thermostat setpoint input
	2 Bytes	I	C - - W -	DPT_Value_Temp	-273.00° - 670760.00°	[T1] Basic Setpoint	Reference setpoint
156	1 Bit	I	C - - W -	DPT_Step	0/1	[T1] Setpoint Step	0=-0.5Å°C; 1=+0.5Å°C
157	2 Bytes	I	C - - W -	DPT_Value_Tempd	-670760,00 - 670760,00	[T1] Setpoint Offset	Float offset value
158	2 Bytes	O	C T R - -	DPT_Value_Temp	-273.00° - 670760.00°	[T1] Setpoint Status	Current setpoint
159	2 Bytes	O	C T R - -	DPT_Value_Temp	-273.00° - 670760.00°	[T1] Basic Setpoint Status	Current basic setpoint
160	2 Bytes	O	C T R - -	DPT_Value_Tempd	-670760,00 - 670760,00	[T1] Setpoint Offset Status	Current setpoint offset
161	1 Bit	I	C - - W -	DPT_Reset	0/1	[T1] Setpoint Reset	Reset setpoint to default
	1 Bit	I	C - - W -	DPT_Reset	0/1	[T1] Offset Reset	Reset offset
162	1 Bit	I	C - - W -	DPT_Heat_Cool	0/1	[T1] Mode	0 = Cool; 1 = Heat
163	1 Bit	O	C T R - -	DPT_Heat_Cool	0/1	[T1] Mode Status	0 = Cool; 1 = Heat
164	1 Bit	I	C - - W -	DPT_Switch	0/1	[T1] On/Off	0=Off; 1=On
165	1 Bit	O	C T R - -	DPT_Switch	0/1	[T1] On/Off Status	0=Off; 1=On
166	1 Byte	O	C T R - -	DPT_Scaling	0% - 100%	[T1] Control Variable (Cool)	PI Control (Continuous)
167	1 Byte	O	C T R - -	DPT_Scaling	0% - 100%	[T1] Control Variable (Heat)	PI Control (Continuous)
168	1 Bit	O	C T R - -	DPT_Switch	0/1	[T1] Control Variable (Cool)	2-Point Control
	1 Bit	O	C T R - -	DPT_Switch	0/1	[T1] Control Variable (Cool)	PI Control (PWM)
169	1 Bit	O	C T R - -	DPT_Switch	0/1	[T1] Control Variable (Heat)	2-Point Control
	1 Bit	O	C T R - -	DPT_Switch	0/1	[T1] Control Variable (Heat)	PI Control (PWM)
170	1 Bit	O	C T R - -	DPT_Switch	0/1	[T1] Additional Cool	Temp >= (Setpoint+Band) => "1"
171	1 Bit	O	C T R - -	DPT_Switch	0/1	[T1] Additional Heat	Temp <= (Setpoint-Band) => "1"
172	1 Bit	O	C T R - -	DPT_Switch	0/1	[T1] PI State (Cool)	0 = PI signal 0%; 1 = PI signal greater than 0%
173	1 Bit	O	C T R - -	DPT_Switch	0/1	[T1] PI State (Heat)	0 = PI signal 0%; 1 = PI signal greater than 0%
174, 178, 182	2 Bytes	O	C T R - -	DPT_Value_Temp	-273.00° - 670760.00°	[In] Current Temperature	Temperature sensor value
175, 179, 183	1 Bit	O	C T R - -	DPT_Alarm	0/1	[In] Overcooling	0 = No Alarm; 1 = Alarm
176, 180, 184	1 Bit	O	C T R - -	DPT_Alarm	0/1	[In] Overheating	0 = No Alarm; 1 = Alarm
177, 181	1 Bit	O	C T R - -	DPT_Alarm	0/1	[In] Probe Error	0 = No Alarm; 1 = Alarm
185	1 Byte	I	C - - W -	DPT_SceneControl	0-63; 128-191	[Motion Sensor] Scene Input	Scene Value
186	1 Byte		C T - - -	DPT_SceneControl	0-63; 128-191	[Motion Sensor] Scene Output	Scene Value
188, 212	1 Bit	O	C T R - -	DPT_Alarm	0/1	[In] Open Circuit Error	0 = No Error; 1 = Open Circuit Error
189, 213	1 Bit	O	C T R - -	DPT_Alarm	0/1	[In] Short Circuit Error	0 = No Error; 1 = Short Circuit Error

190, 214	1 Byte	O	C T R - -	DPT_Scaling	0% - 100%	[In] Presence State (Scaling)	0-100%
191, 215	1 Byte	O	C T R - -	DPT_HVACMode	1=Comfort 2=Standby 3=Economy 4=Building Protection	[In] Presence State (HVAC)	Auto, Comfort, Standby, Economy, Building Protection
192, 216	1 Bit	O	C T R - -	DPT_Occupancy	0/1	[In] Presence State (Binary)	Binary Value
	1 Bit	O	C T R - -	DPT_Trigger	0/1	[In] Presence: Slave Output	1 = Motion Detected
193, 217	1 Bit	I	C - - W -	DPT_Trigger	0/1	[In] Presence Trigger	Binary Value to Trigger the Presence Detection
194, 218	1 Bit	I	C - - W -	DPT_Trigger	0/1	[In] Presence: Slave Input	0 = Nothing; 1 = Detection from slave device
195, 219	1 Bit	I	C - - W -	DPT_Trigger	0/1	[In] External Motion Detection	0 = Nothing; 1 = Motion detected by an external sensor
196, 201, 206, 220, 230	1 Byte	O	C T R - -	DPT_Scaling	0% - 100%	[In] [Cm] Detection State (Scaling)	0-100%
197, 202, 207, 221, 231	1 Byte	O	C T R - -	DPT_HVACMode	1=Comfort 2=Standby 3=Economy 4=Building Protection	[In] [Cm] Detection State (HVAC)	Auto, Comfort, Standby, Economy, Building Protection
198, 203, 208, 222, 232	1 Bit	O	C T R - -	DPT_Switch	0/1	[In] [Cm] Detection State (Binary)	Binary Value
199, 204, 209, 223, 233	1 Bit	I	C - - W -	DPT_Switch	0/1	[In] [Cm] Channel Lock	According to parameters
200, 205, 210, 224, 234	1 Bit	I	C - - W -	DPT_Switch	0/1	[In] [Cm] Force State	0 = No Detection; 1 = Detection
235, 241	1 Bit	I	C - - W -	DPT_Switch	0/1	[In] Input Lock	1 = Locked; 0 = Unlocked
236, 242	1 Bit		C T - - -	DPT_Switch	0/1	[In] [Short Press] 0	Sending of 0
	1 Bit		C T - - -	DPT_Switch	0/1	[In] [Short Press] 1	Sending of 1
	1 Bit	I	C T - W -	DPT_Switch	0/1	[In] [Short Press] 0/1 Switching	Switching 0/1
	1 Bit		C T - - -	DPT_UpDown	0/1	[In] [Short Press] Move Up Shutter	Sending of 0 (Up)
	1 Bit		C T - - -	DPT_UpDown	0/1	[In] [Short Press] Move Down Shutter	Sending of 1 (Down)
	1 Bit		C T - - -	DPT_UpDown	0/1	[In] [Short Press] Move Up/Down Shutter	Switching 0/1 (Up/Down)
	1 Bit		C T - - -	DPT_Step	0/1	[In] [Short Press] Stop/Step Up Shutter	Sending of 0 (Stop/Step up)
	1 Bit		C T - - -	DPT_Step	0/1	[In] [Short Press] Stop/Step Down Shutter	Sending of 1 (Stop/Step down)
	1 Bit		C T - - -	DPT_Step	0/1	[In] [Short Press] Stop/Step Shutter (switched)	Switching of 0/1 (Stop/Step up/down)
	4 Bit		C T - - -	DPT_Control_Dimming	0x0 (Stop) 0x1 (Dec. by 100%) 0x2 (Dec. by 50%) ... 0x8 (Stop) 0x9 (Inc. by 100%) 0xA (Inc. by 50%) ... 0xF (Inc. by 1%)	[In] [Short Press] Brighter	Increase Brightness

	4 Bit		CT---	DPT_Control_Dimming	0x0 (Stop) 0x1 (Dec. by 100%) 0x2 (Dec. by 50%) ... 0x8 (Stop) 0x9 (Inc. by 100%) 0xA (Inc. by 50%) ... 0xF (Inc. by 1%)	[In] [Short Press] Darker	Decrease Brightness
	4 Bit		CT---	DPT_Control_Dimming	0x0 (Stop) 0x1 (Dec. by 100%) 0x2 (Dec. by 50%) ... 0x8 (Stop) 0x9 (Inc. by 100%) 0xA (Inc. by 50%) ... 0xF (Inc. by 1%)	[In] [Short Press] Brighter/Darker	Switch Bright/Dark
	1 Bit		CT---	DPT_Switch	0/1	[In] [Short Press] Dimmer ON	Sending of 1 (ON)
	1 Bit		CT---	DPT_Switch	0/1	[In] [Short Press] Dimmer OFF	Sending of 0 (OFF)
	1 Bit	I	CT-W-	DPT_Switch	0/1	[In] [Short Press] Dimmer ON/OFF	Switching 0/1
	1 Byte		CT---	DPT_SceneControl	0-63; 128-191	[In] [Short Press] Run Scene	Sending of 0 - 63
	1 Byte		CT---	DPT_SceneControl	0-63; 128-191	[In] [Short Press] Save Scene	Sending of 128 - 191
	1 Bit	I/O	CTRW-	DPT_Switch	0/1	[In] [Switch/Sensor] Edge	Sending of 0 or 1
	1 Byte		CT---	DPT_Value_1_Ucount	0 - 255	[In] [Short Press] Constant Value (Integer)	0 - 255
	1 Byte		CT---	DPT_Scaling	0% - 100%	[In] [Short Press] Constant Value (Percentage)	0% - 100%
	2 Bytes		CT---	DPT_Value_2_Ucount	0 - 65535	[In] [Short Press] Constant Value (Integer)	0 - 65535
	2 Bytes		CT---	9.xxx	-671088.64 - 670760.96	[In] [Short Press] Constant Value (float)	Float value
237, 243	1 Byte	I	C--W-	DPT_Scaling	0% - 100%	[In] [Short Press] Shutter Status (input)	0% = Top; 100% = Bottom
	1 Byte	I	C--W-	DPT_Scaling	0% - 100%	[In] [Short Press] Dimming Status (input)	0% - 100%
238, 244	1 Bit		CT---	DPT_Switch	0/1	[In] [Long Press] 0	Sending of 0
	1 Bit		CT---	DPT_Switch	0/1	[In] [Long Press] 1	Sending of 1
	1 Bit	I	CT-W-	DPT_Switch	0/1	[In] [Long Press] 0/1 Switching	Switching 0/1
	1 Bit		CT---	DPT_UpDown	0/1	[In] [Long Press] Move Up Shutter	Sending of 0 (Up)
	1 Bit		CT---	DPT_UpDown	0/1	[In] [Long Press] Move Down Shutter	Sending of 1 (Down)
	1 Bit		CT---	DPT_UpDown	0/1	[In] [Long Press] Move Up/Down Shutter	Switching 0/1 (Up/Down)
	1 Bit		CT---	DPT_Step	0/1	[In] [Long Press] Stop/Step Up Shutter	Sending of 0 (Stop/Step up)
	1 Bit		CT---	DPT_Step	0/1	[In] [Long Press] Stop/Step Down Shutter	Sending of 1 (Stop/Step down)
	1 Bit		CT---	DPT_Step	0/1	[In] [Long Press] Stop/Step Shutter (switched)	Switching of 0/1 (Stop/Step up/down)
	4 Bit		CT---	DPT_Control_Dimming	0x0 (Stop) 0x1 (Dec. by 100%)	[In] [Long Press] Brighter	Long Pr. -> Brighter; Release -> Stop

					0x2 (Dec. by 50%) ... 0x8 (Stop) 0x9 (Inc. by 100%) 0xA (Inc. by 50%) ... 0xF (Inc. by 1%)		
	4 Bit		CT----	DPT_Control_Dimming	0x0 (Stop) 0x1 (Dec. by 100%) 0x2 (Dec. by 50%) ... 0x8 (Stop) 0x9 (Inc. by 100%) 0xA (Inc. by 50%) ... 0xF (Inc. by 1%)	[In] [Long Press] Darker	Long Pr. -> Darker; Release -> Stop
	4 Bit		CT----	DPT_Control_Dimming	0x0 (Stop) 0x1 (Dec. by 100%) 0x2 (Dec. by 50%) ... 0x8 (Stop) 0x9 (Inc. by 100%) 0xA (Inc. by 50%) ... 0xF (Inc. by 1%)	[In] [Long Press] Brighter/Darker	Long Pr. -> Brighter/Darker; Release -> Stop
	1 Bit		CT----	DPT_Switch	0/1	[In] [Long Press] Dimmer ON	Sending of 1 (ON)
	1 Bit		CT----	DPT_Switch	0/1	[In] [Long Press] Dimmer OFF	Sending of 0 (OFF)
	1 Bit	I	CT-W-	DPT_Switch	0/1	[In] [Long Press] Dimmer ON/OFF	Switching 0/1
	1 Byte		CT----	DPT_SceneControl	0-63; 128-191	[In] [Long Press] Run Scene	Sending of 0 - 63
	1 Byte		CT----	DPT_SceneControl	0-63; 128-191	[In] [Long Press] Save Scene	Sending of 128 - 191
	1 Bit	O	CTR--	DPT_Alarm	0/1	[In] [Switch/Sensor] Alarm: Breakdown or sabotage	1 = Alarm; 0 = No Alarm
	2 Bytes		CT----	9.xxx	-671088.64 - 670760.96	[In] [Long Press] Constant Value (float)	Float value
	2 Bytes		CT----	DPT_Value_2_Ucount	0 - 65535	[In] [Long Press] Constant Value (Integer)	0 - 65535
	1 Byte		CT----	DPT_Scaling	0% - 100%	[In] [Long Press] Constant Value (Percentage)	0% - 100%
	1 Byte		CT----	DPT_Value_1_Ucount	0 - 255	[In] [Long Press] Constant Value (Integer)	0 - 255
239, 245	1 Bit		CT----	DPT_Trigger	0/1	[In] [Long Press/Release] Stop Shutter	Release -> Stop Shutter
240, 246	1 Byte	I	C--W-	DPT_Scaling	0% - 100%	[In] [Long Press] Dimming Status (input)	0% - 100%
	1 Byte	I	C--W-	DPT_Scaling	0% - 100%	[In] [Long Press] Shutter Status (input)	0% = Top; 100% = Bottom
241	1 Bit	I	C--W-	DPT_Switch	0/1	[In] Input Lock	1 = Locked; 0 = Unlocked

Join and send us your inquiries
about Zennio devices:

<http://zennioenglish.zendesk.com>

Zennio Avance y Tecnología S.L.
C/ Río Jarama, 132. Nave P-8.11
45007 Toledo (Spain).

Tel. +34 925 232 002.
Fax. +34 925 337 310.

www.zennio.com
info@zennio.com